



SPC BENCHMARK 1TM Full Disclosure Report

DELL, INC. Dell EqualLogic PS6210XV Array

SPC-1 V1.14

Submitted for Review: June 9, 2014 Submission Identifier: A00144

First Edition – June 2014

THE INFORMATION CONTAINED IN THIS DOCUMENT IS DISTRIBUTED ON AN AS IS BASIS WITHOUT ANY WARRANTY EITHER EXPRESS OR IMPLIED. The use of this information or the implementation of any of these techniques is the customer's responsibility and depends on the customer's ability to evaluate and integrate them into the customer's operational environment. While each item has been reviewed by Dell, Inc. for accuracy in a specific situation, there is no guarantee that the same or similar results will be obtained elsewhere. Customers attempting to adapt these techniques to their own environment do so at their own risk.

This publication was produced in the United States. Dell, Inc. may not offer the products, services, or features discussed in this document in other countries, and the information is subject to change with notice. Consult your local Dell, Inc. representative for information on products and services available in your area.

© Copyright Dell, Inc. 2014. All rights reserved.

Permission is hereby granted to reproduce this document in whole or in part, provided the copyright notice as printed above is set forth in full text on the title page of each item reproduced.

Trademarks

SPC Benchmark-1, SPC-1, SPC-1 IOPS, SPC-1 LRT and SPC-1 Price-Performance are trademarks of the Storage Performance Council. Dell, EqualLogic and the Dell logo are trademarks or registered trademarks of Dell, Inc. in the United States and other countries. All other brands, trademarks, and product names are the property of their respective owners.

Table of Contents

Audit Certificationvii
Audit Certification (cont.)viii
Letter of Good Faithix
Executive Summary10
Test Sponsor and Contact Information10
Revision Information and Key Dates10
Tested Storage Product (TSP) Description11
Summary of Results12
Storage Capacities, Relationships, and Utilization13
Response Time – Throughput Curve16
Response Time – Throughput Data16
Priced Storage Configuration Pricing17
Differences between the Tested Storage Configuration (TSC) and Priced Storage Configuration17
Priced Storage Configuration Diagram18
Priced Storage Configuration Components18
Configuration Information19
Benchmark Configuration (BC)/Tested Storage Configuration (TSC) Diagram.19
Storage Network Configuration19
Host System(s) and Tested Storage Configuration (TSC) Table of Components 19
Benchmark Configuration/Tested Storage Configuration Diagram20
Host System and Tested Storage Configuration Components21
Customer Tunable Parameters and Options22
Tested Storage Configuration (TSC) Description22
SPC-1 Workload Generator Storage Configuration22
ASU Pre-Fill23
SPC-1 Data Repository24
Storage Capacities and Relationships24
SPC-1 Storage Capacities
SPC-1 Storage Hierarchy Ratios25
SPC-1 Storage Capacity Charts25
Storage Capacity Utilization27
Logical Volume Capacity and ASU Mapping28
SPC-1 Benchmark Execution Results29
SPC-1 Tests, Test Phases, and Test Runs29

"Ramp-Up" Test Runs	30
Primary Metrics Test – Sustainability Test Phase	30
SPC-1 Workload Generator Input Parameters	31
Sustainability Test Results File	31
Sustainability – Data Rate Distribution Data (MB/second)	31
Sustainability – Data Rate Distribution Graph	31
Sustainability – I/O Request Throughput Distribution Data	32
Sustainability – I/O Request Throughput Distribution Graph	32
Sustainability – Average Response Time (ms) Distribution Data	33
Sustainability – Average Response Time (ms) Distribution Graph	33
Sustainability – Response Time Frequency Distribution Data	34
Sustainability – Response Time Frequency Distribution Graph	34
Sustainability – Measured Intensity Multiplier and Coefficient of Variation	35
Primary Metrics Test – IOPS Test Phase	36
SPC-1 Workload Generator Input Parameters	36
IOPS Test Results File	36
IOPS Test Run – I/O Request Throughput Distribution Data	37
IOPS Test Run – I/O Request Throughput Distribution Graph	37
IOPS Test Run – Average Response Time (ms) Distribution Data	38
IOPS Test Run – Average Response Time (ms) Distribution Graph	38
IOPS Test Run –Response Time Frequency Distribution Data	39
IOPS Test Run –Response Time Frequency Distribution Graph	39
IOPS Test Run – I/O Request Information	40
IOPS Test Run – Measured Intensity Multiplier and Coefficient of Variation	40
Primary Metrics Test – Response Time Ramp Test Phase	41
SPC-1 Workload Generator Input Parameters	41
Response Time Ramp Test Results File	41
Response Time Ramp Distribution (IOPS) Data	42
Response Time Ramp Distribution (IOPS) Data (continued)	43
Response Time Ramp Distribution (IOPS) Graph	43
SPC-1 LRT [™] Average Response Time (ms) Distribution Data	44
SPC-1 LRT [™] Average Response Time (ms) Distribution Graph	44
SPC-1 LRT [™] (10%) – Measured Intensity Multiplier and Coefficient of Variation	45
Repeatability Test	46
SPC-1 Workload Generator Input Parameters	46
Repeatability Test Results File	47
Repeatability 1 LRT – I/O Request Throughput Distribution Data	48
Repeatability 1 LRT – I/O Request Throughput Distribution Graph	48
Repeatability 1 LRT –Average Response Time (ms) Distribution Data	49

FULL DISCLOSURE REPORT

Repeatability 1 LRT –Average Response Time (ms) Distribution Graph	49
Repeatability 1 IOPS – I/O Request Throughput Distribution Data	50
Repeatability 1 IOPS – I/O Request Throughput Distribution Graph	50
Repeatability 1 IOPS –Average Response Time (ms) Distribution Data	51
Repeatability 1 IOPS –Average Response Time (ms) Distribution Graph	51
Repeatability 2 LRT – I/O Request Throughput Distribution Data	52
Repeatability 2 LRT – I/O Request Throughput Distribution Graph	52
Repeatability 2 LRT –Average Response Time (ms) Distribution Data	53
Repeatability 2 LRT –Average Response Time (ms) Distribution Graph	53
Repeatability 2 IOPS – I/O Request Throughput Distribution Data	54
Repeatability 2 IOPS – I/O Request Throughput Distribution Graph	54
Repeatability 2 IOPS –Average Response Time (ms) Distribution Data	55
Repeatability 2 IOPS –Average Response Time (ms) Distribution Graph	55
Repeatability 1 (LRT) Measured Intensity Multiplier and Coefficient of Variation	56
Repeatability 1 (IOPS) Measured Intensity Multiplier and Coefficient of Variation	56
Repeatability 2 (LRT) Measured Intensity Multiplier and Coefficient of Variation	56
Repeatability 2 (IOPS) Measured Intensity Multiplier and Coefficient of Variation	57
Data Persistence Test	58
SPC-1 Workload Generator Input Parameters	58
Data Persistence Test Results File	58
Data Persistence Test Results	59
Priced Storage Configuration Availability Date	. 60
Pricing Information	. 60
Tested Storage Configuration (TSC) and Priced Storage Configuration	
Differences	. 60
Anomalies or Irregularities	60
Appendix A: SPC-1 Glossary	61
"Decimal" (powers of ten) Measurement Units	61
"Binary" (powers of two) Measurement Units	61
SPC-1 Data Repository Definitions	61
SPC-1 Data Protection Levels	62
SPC-1 Test Execution Definitions	62
I/O Completion Types	64
SPC-1 Test Run Components	64
Appendix B: Customer Tunable Parameters and Options	
•	. 65
Appendix C: Tested Storage Configuration (TSC) Creation	. 65
Appendix C: Tested Storage Configuration (TSC) Creation Starting the Group Manager GUI:	65 66 66

Create Custom Storage Pool	67
Creating SPC-1 Volumes	71
Cloning a Volume (logical units 2 through 10)	75
Preparing the Volumes on the single Host System	78
Appendix D: SPC-1 Workload Generator Storage Commands and	
Parameters	80
ASU Pre-Fill	80
Primary Metrics, Repeatability and SPC-1 Persistence Tests	81
Appendix E: SPC-1 Workload Generator Input Parameters	82
SPC-1 Persistence Test Run 2	82

AUDIT CERTIFICATION



AUDIT CERTIFICATION (CONT.)

Dell EqualLogic PS6210XV Array Page 2 SPC-1 Audit Certification Physical verification of the components to match the above diagram. Listings and commands to configure the Benchmark Configuration/Tested Storage Configuration, including customer tunable parameters that were changed from default values. SPC-1 Workload Generator commands and parameters used for the audited SPC Test Runs. The following Host System requirements were verified by physical inspection and information supplied by Dell, Inc.: ✓ The type of Host System including the number of processors and main memory. ✓ The presence and version number of the SPC-1 Workload Generator on the Host System. ✓ The TSC boundary within the Host System. The execution of each Test, Test Phase, and Test Run was observed and found compliant with all of the requirements and constraints of Clauses 4, 5, and 11 of the SPC-1 Benchmark Specification. The Test Results Files and resultant Summary Results Files received from Dell, Inc. for each of following were authentic, accurate, and compliant with all of the requirements and constraints of Clauses 4 and 5 of the SPC-1 Benchmark Specification: ✓ Data Persistence Test 1 Sustainability Test Phase IOPS Test Phase 1 ✓ Response Time Ramp Test Phase ✓ Repeatability Test There were no differences between the Tested Storage Configuration and Priced Storage Configuration. The submitted pricing information met all of the requirements and constraints of Clause 8 of the SPC-1 Benchmark Specification. The Full Disclosure Report (FDR) met all of the requirements in Clause 9 of the SPC-1 Benchmark Specification. This successfully audited SPC measurement is not subject to an SPC Confidential Review. Audit Notes: There were no audit notes or exceptions. Respectfully, Walter E. Baker Walter E. Baker SPC Auditor Storage Performance Council 643 Bair Island Road, Suite 103 Redwood City, CA 94062 AuditService@storageperformance.org 650.556.9384

FULL DISCLOSURE REPORT

LETTER OF GOOD FAITH

Dell Inc. 300 Innovative Way Nashua, NH 03062 USA tel +1 603 579 9762 fax +1 603 589 5598 www.dell.com Mr. Walter E. Baker, SPC Auditor Gradient Systems 643 Bair Island Road, Suite 103 Redwood City, CA 94063-2755 April 16, 2014 Subject: SPC-1 Letter of Good Faith for the Dell EqualLogic PS6210XV-3 Array SAN Dell Inc. is the SPC-1 Test Sponsor for the above listed product. To the best of our knowledge and belief, the required SPC-1 benchmark results and materials we have submitted for that product are complete, accurate, and in full compliance with v1.14 of the SPC-1 benchmark specification. In addition, we have reported any items in the Benchmark Configuration and execution of the benchmark that affected the reported results even if the items are not explicitly required to be disclosed by the SPC-1 benchmark specification. Sincerely, 9 10 Alan Atkinson Vice President/General Manager **Dell Storage**

EXECUTIVE SUMMARY

Test Sponsor and Contact Information

	Test Sponsor and Contact Information
Test Sponsor Primary Contact	Dell, Inc. – <u>http://www.dell.com</u> Matt Reichow – <u>Matt_Reichow@dell.com</u> 7625 Smetana Ln. Eden Prairie, MN 55344 Phone: (952) 567-6691 FAX:
Test Sponsor Alternate Contact	Dell, Inc. – <u>http://www.dell.com</u> Scott Saktanaset – <u>Scott_Saktanaset@dell.com</u> 300 Innovative Way Nashua, NH 03062 Phone: (603) 589-5661 FAX: (603) 589-5598
Test Sponsor Alternate Contact	Dell, Inc. – <u>http://www.dell.com</u> Suresh Jasrasaria – <u>Suresh_Jasrasaris@dell.com</u> 300 Innovative Way Nashua, NH 03062 Phone: (603) 589-5689 FAX: (603) 589-5598
Auditor	Storage Performance Council – <u>http://www.storageperformance.org</u> Walter E. Baker – <u>AuditService@StoragePerformance.org</u> 643 Bair Island Road, Suite 103 Redwood City, CA 94063 Phone: (650) 556-9384 FAX: (650) 556-9385

Revision Information and Key Dates

Revision Information and Key Dates		
SPC-1 Specification revision number	V1.14	
SPC-1 Workload Generator revision number	V2.3.0	
Date Results were first used publicly	June 9, 2014	
Date the FDR was submitted to the SPC	June 9, 2014	
Date the Priced Storage Configuration is available for shipment to customers	currently available	
Date the TSC completed audit certification	June 6, 2014	

Tested Storage Product (TSP) Description

Built on an advanced, peer storage architecture, EqualLogic storage simplifies the deployment and administration of consolidated storage environments, enabling:

- Perpetual self-optimization with automated load balancing across disks, RAID sets, connections, cache and controllers.
- Efficient enterprise scalability for both performance and capacity without fork-lift upgrades.
- Powerful, intelligent and simplified management.
- Improved productivity and streamlined IT infrastructure through unified block and file storage capabilities.

What's more, EqualLogic products include a comprehensive software portfolio with easy-touse array software, host integration tools and no licensing fees. EqualLogic virtualizedstorage offers a simple path to rapid deployment, comprehensive data protection, enterprise-class performance and reliability, and seamless pay-as-you grow expansion. All EqualLogic PS Series arrays are completely interoperable and can be mixed and matched to build tiered storage within a single storage pool or across multiple pools.

EqualLogic PS6210 Series arrays bring a new level of performance to service more of your most demanding applications and virtualization requirements, while delivering the simplicity of the EqualLogic management experience. Featuring six array configurations, including 2U/2.5" drive options with All Flash and Hybrid Arrays, it is ideal for companies and organizations with growing data and performance needs.

SPC-1 Reported Data			
Tested Storage Product (TSP) Name: Dell EqualLogic PS6210XV Array			
Metric Reported Result			
SPC-1 IOPS™	25,147.22		
SPC-1 Price-Performance™	\$3.87/SPC-1 IOPS™		
Total ASU Capacity	6,023.786 GB		
Data Protection Level	Protected 2 (mirroring)		
Total Price	\$97,402.81		
Currency Used	U.S. Dollars		
Target Country for availability, sales and support	USA		

Summary of Results

SPC-1 IOPS[™] represents the maximum I/O Request Throughput at the 100% load point.

SPC-1 Price-Performance[™] is the ratio of Total Price to SPC-1 IOPS[™].

Total ASU (Application Storage Unit) **Capacity** represents the total storage capacity available to be read and written in the course of executing the SPC-1 benchmark.

A **Data Protection Level** of **Protected 2** using *Mirroring* configures two or more identical copies of user data.

Protected 2: The single point of failure of any **component** in the configuration will not result in permanent loss of access to or integrity of the SPC-1 Data Repository.

Total Price includes the cost of the Priced Storage Configuration plus three years of hardware maintenance and software support as detailed on page 17.

Currency Used is formal name for the currency used in calculating the Total Price and SPC-1 Price-PerformanceTM. That currency may be the local currency of the Target Country or the currency of a difference country (non-local currency).

The **Target Country** is the country in which the Priced Storage Configuration is available for sale and in which the required hardware maintenance and software support is provided either directly from the Test Sponsor or indirectly via a third-party supplier.

Storage Capacities, Relationships, and Utilization

The following four charts and table document the various storage capacities, used in this benchmark, and their relationships, as well as the storage utilization values required to be reported.

The capacity values in each of the following four charts are listed as integer values, for readability, rather than the decimal values listed elsewhere in this document.







SPC BENCHMARK 1[™] V1.14 Dell, Inc. Dell EqualLogic PS6210XV Array FULL DISCLOSURE REPORT



SPC-1 Storage Capacity	Utilization
Application Utilization	27.89%
Protected Application Utilization	55.77%
Unused Storage Ratio	30.96%

Application Utilization: Total ASU Capacity (6,023.786 GB) divided by Physical Storage Capacity (21,601.657 GB).

Protected Application Utilization: (Total ASU Capacity (6,023.786 GB) plus total Data Protection Capacity (9,367.839 GB) minus unused Data Protection Capacity (3,344.072 GB)) divided by Physical Storage Capacity (21,601.657 GB).

Unused Storage Ratio: Total Unused Capacity (6,688.143 GB) divided by Physical Storage Capacity (21,601.657 GB) and may not exceed 45%.

Detailed information for the various storage capacities and utilizations is available on pages 24-25.

Response Time – Throughput Curve

The Response Time-Throughput Curve illustrates the Average Response Time (milliseconds) and I/O Request Throughput at 100%, 95%, 90%, 80%, 50%, and 10% of the workload level used to generate the SPC-1 IOPSTM metric.

The Average Response Time measured at any of the above load points cannot exceed 30 milliseconds or the benchmark measurement is invalid.



Response Time – Throughput Data

	10% Load	50% Load	80% Load	90% Load	95% Load	100% Load
I/O Request Throughput	2,501.17	12,555.69	20,100.50	22,593.98	23,847.64	25,147.22
Average Response Time (ms):						
All ASUs	2.25	3.33	4.43	4.86	6.78	8.30
ASU-1	3.03	4.46	5.68	6.18	8.55	10.41
ASU-2	2.39	4.41	7.45	8.56	12.65	15.95
ASU-3	0.52	0.45	0.44	0.45	0.46	0.48
Reads	4.59	6.94	9.73	10.83	15.63	19.43
Writes	0.72	0.98	0.97	0.97	1.02	1.05

	Part		Discount	Reference	Extended
Quantity	Number	Description	Percentage	Price	Price
		Dell EqualLogic PS6210XV, 2 controller nodes, each			
		with 16GB non-volatile cache of memory, 2			
		10GBASE-T RJ45 auto-sensing (10Gb/1Gb/100Mb)			
		ports, 2 10GbE SFP+ ports for fibre or copper			
		cabling, 24 300GB 15k 2.5″ SAS drives + 3 Yr Pro			
3	210-ABPJ	Support Maintenance	43%	\$48,372.00	\$82,716.12
		Dell PowerConnect 8132 SFP Layer 3 10GbE + 3 Yr			
2	225-3586	Pro Support Maintenance	55%	\$15,813.00	\$14,231.70
1	A3612382	Intel E10G42BTDA Server Adapter X520-DA2 10Gbps	9%	\$ 499.99	\$ 454.99
		Total System Price			\$97,402.81

Priced Storage Configuration Pricing

The above pricing includes hardware maintenance and software support for three years, 7 days per week, 24 hours per day. The hardware maintenance and software support provides the following:

- Acknowledgement of new and existing problems within four (4) hours.
- Onsite presence of a qualified maintenance engineer or provision of a customer replaceable part within four (4) hours of the above acknowledgement for any hardware failure that results in an inoperative Price Storage Configuration that can be remedied by the repair or replacement of a Priced Storage Configuration component.

Differences between the Tested Storage Configuration (TSC) and Priced Storage Configuration

A second Dell PowerConnect 10GbE switch was included in the Priced Storage Configuration as a spare to fulfill one of the requirements for a data protection level of **Protected 2**.

Priced Storage Configuration Diagram



3 – Dell EqualLogic PS6210XV Arrays

72 - 300GB, 2.5", 15K RPM, SAS HDDs (24 HDDs per Array)

Priced Storage Configuration Components

Priced Storage Configuration
1 – Intel E10G42BTDA Server Adapter X520-DA2 10Gbps
2 – Dell PowerConnect PC8132 10GbE Switches (second switch included as a spare)
3 – Dell EqualLogic PS6210XV Arrays
each array with:
2 – controller nodes with 16 GB cache (6 controller nodes total)
2 – 10GBASE-T auto-sensing (10Gb/1Gb/100Mb) ports (6 ports total)
2 – 10GbE SFP+ front-end ports (6 ports total, 6 ports used)
1 – 6Gb SAS connection (3 total, 3 used)
24 – 300 GB, 2.5", 15K RPM, SAS HDDs (72 HDDs total)

In each of the following sections of this document, the appropriate Full Disclosure Report requirement, from the SPC-1 benchmark specification, is stated in italics followed by the information to fulfill the stated requirement.

CONFIGURATION INFORMATION

Benchmark Configuration (BC)/Tested Storage Configuration (TSC) Diagram

<u>Clause 9.4.3.4.1</u>

A one page Benchmark Configuration (BC)/Tested Storage Configuration (TSC) diagram shall be included in the FDR...

The Benchmark Configuration (BC)/Tested Storage Configuration (TSC) is illustrated on page <u>20</u> (*Benchmark Configuration/Tested Storage Configuration Diagram*).

Storage Network Configuration

Clause 9.4.3.4.1

•••

5. If the TSC contains network storage, the diagram will include the network configuration. If a single diagram is not sufficient to illustrate both the Benchmark Configuration and network configuration in sufficient detail, the Benchmark Configuration diagram will include a high-level network illustration as shown in Figure 9-8. In that case, a separate, detailed network configuration diagram will also be included as described in Clause 9.4.3.4.2.

<u>Clause 9.4.3.4.2</u>

If a storage network was configured as a part of the Tested Storage Configuration and the Benchmark Configuration diagram described in Clause 9.4.3.4.1 contains a high-level illustration of the network configuration, the Executive Summary will contain a one page topology diagram of the storage network as illustrated in Figure 9-9.

The storage network portion of the Benchmark Configuration(BC)/Tested Storage Configuration (TSC) is illustrated on page <u>20</u> (<u>Benchmark Configuration/Tested Storage</u> <u>Configuration Diagram</u>).

Host System(s) and Tested Storage Configuration (TSC) Table of Components

<u>Clause 9.4.3.4.3</u>

The FDR will contain a table that lists the major components of each Host System and the Tested Storage Configuration (TSC).

The Host System(s) and TSC table of components may be found on page <u>21</u> (<u>Host System</u> <u>and Tested Storage Configuration Components</u>).

Benchmark Configuration/Tested Storage Configuration Diagram



Host System and Tested Storage Configuration Components

Host System
1 – Dell PowerEdge R620 rack server, with:
2 – Intel® Xeon® 2.20 GHz E502660 processors
each with 8 cores and 2.5 MB cache per core
128 GB main memory
Windows Server 2008 R2 Enterprise with SP1
PCIe 3.0
Tested Storage Configuration (TSC) Components
1 – Intel E10G42BTDA Server Adapter X520-DA2 10Gbps
1 – Dell PowerConnect PC8132 10GbE Switche
3 – Dell EqualLogic PS6210XV Arrays
each array with:
2 – controller nodes with 16 GB cache
(6 controller nodes total)
2 – 10GBASE-T auto-sensing (10Gb/1Gb/100Mb) ports (6 ports total)
2 – 10GbE SFP+ front-end ports
(6 ports total, 6 ports used)
1 – 6Gb SAS connection (3 total, 3 used)
24 – 300 GB, 2.5", 15K RPM, SAS HDDs (72 HDDs total)

Customer Tunable Parameters and Options

<u>Clause 9.4.3.5.1</u>

All Benchmark Configuration (BC) components with customer tunable parameter and options that have been altered from their default values must be listed in the FDR. The FDR entry for each of those components must include both the name of the component and the altered value of the parameter or option. If the parameter name is not self-explanatory to a knowledgeable practitioner, a brief description of the parameter's use must also be included in the FDR entry.

<u>Appendix B: Customer Tunable Parameters and Options</u> on page <u>65</u> contains the customer tunable parameters and options that have been altered from their default values for this benchmark.

Tested Storage Configuration (TSC) Description

<u>Clause 9.4.3.5.2</u>

The FDR must include sufficient information to recreate the logical representation of the TSC. In addition to customer tunable parameters and options (Clause 4.2.4.5.3), that information must include, at a minimum:

- A diagram and/or description of the following:
 - > All physical components that comprise the TSC. Those components are also illustrated in the BC Configuration Diagram in Clause 9.2.4.4.1 and/or the Storage Network Configuration Diagram in Clause 9.2.4.4.2.
 - > The logical representation of the TSC, configured from the above components that will be presented to the Workload Generator.
- Listings of scripts used to create the logical representation of the TSC.
- If scripts were not used, a description of the process used with sufficient detail to recreate the logical representation of the TSC.

<u>Appendix C: Tested Storage Configuration (TSC) Creation</u> on page <u>66</u> contains the detailed information that describes how to create and configure the logical TSC.

SPC-1 Workload Generator Storage Configuration

<u>Clause 9.4.3.5.3</u>

The FDR must include all SPC-1 Workload Generator storage configuration commands and parameters.

The SPC-1 Workload Generator storage configuration commands and parameters for this measurement appear in <u>Appendix D: SPC-1 Workload Generator Storage Commands and</u> <u>Parameters</u> on page <u>80</u>.

ASU Pre-Fill

<u>Clause 5.3.3</u>

Each of the three SPC-1 ASUs (ASU-1, ASU-2 and ASU-3) is required to be completely filled with specified content prior to the execution of audited SPC-1 Tests. The content is required to consist of random data pattern such as that produced by an SPC recommended tool.

The configuration file used to complete the required ASU pre-fill appears in <u>Appendix</u> D: <u>SPC-1 Workload Generator Storage Commands and Parameters</u> on page <u>80</u>.

SPC-1 DATA REPOSITORY

This portion of the Full Disclosure Report presents the detailed information that fully documents the various SPC-1 storage capacities and mappings used in the Tested Storage Configuration. <u>SPC-1 Data Repository Definitions</u> on page <u>61</u> contains definitions of terms specific to the SPC-1 Data Repository.

Storage Capacities and Relationships

<u>Clause 9.4.3.6.1</u>

Two tables and four charts documenting the storage capacities and relationships of the SPC-1 Storage Hierarchy (Clause 2.1) shall be included in the FDR. ... The capacity value in each chart may be listed as an integer value, for readability, rather than the decimal value listed in the table below.

SPC-1 Storage Capacities

The Physical Storage Capacity consisted of 21,601.657 GB distributed over 72 disk drives (HDDs), 48 disk drives with a formatted capacity of 300 GB and 24 disk drives with a formatted capacity of 300.069 GB. There was 0.000 GB (0.00%) of Unused Storage within the Physical Storage Capacity. Global Storage Overhead consisted of 1,065.841 GB (4.93%) of the Physical Storage Capacity. There was 6,688.143 GB (32.57%) of Unused Storage within the Configured Storage Capacity. The Total ASU Capacity utilized 100.00% of the Addressable Storage Capacity resulting in 0.000 GB (0.00%) of Unused Storage within the Addressable Storage Capacity. The Data Protection (*Mirroring*) capacity was 9,367.839 GB of which 6,023.767 GB was utilized. The total Unused Storage capacity was 6,688.143 GB.

Note: The configured Storage Devices may include additional storage capacity reserved for system overhead, which is not accessible for application use. That storage capacity may not be included in the value presented for Physical Storage Capacity.

SPC-1 Storage Capacities						
Storage Hierarchy Component	Units	Capacity				
Total ASU Capacity	Gigabytes (GB)	6,023.786				
Addressable Storage Capacity	Gigabytes (GB)	6,023.686				
Configured Storage Capacity	Gigabytes (GB)	20,535.816				
Physical Storage Capacity	Gigabytes (GB)	21,601.657				
Data Protection (Mirroring)	Gigabytes (GB)	9,367.839				
Required Storage (metadata/overhead/spares)	Gigabytes (GB)	1,800.138				
Global Storage Overhead	Gigabytes (GB)	1,065.841				
Total Unused Storage	Gigabytes (GB)	6,688.143				

SPC-1 Storage Hierarchy Ratios

	Addressable Storage Capacity	Configured Storage Capacity	Physical Storage Capacity
Total ASU Capacity	100.00%	29.33%	27.89%
Required for Data Protection (Mirroring)		45.62%	43.37%
Addressable Storage Capacity		29.33%	27.89%
Required Storage (spares, overhead)		8.77%	8.33%
Configured Storage Capacity			95.07%
Global Storage Overhead			4.93%
Unused Storage:			
Addressable	0.00%		
Configured		32.57%	
Physical			0.00%

SPC-1 Storage Capacity Charts







SPC BENCHMARK 1[™] V1.14 Dell, Inc. Dell EqualLogic PS6210XV Array FULL DISCLOSURE REPORT



Storage Capacity Utilization

Clause 9.4.3.6.2

The FDR will include a table illustrating the storage capacity utilization values defined for Application Utilization (Clause 2.8.1), Protected Application Utilization (Clause 2.8.2), and Unused Storage Ratio (Clause 2.8.3).

<u>Clause 2.8.1</u>

Application Utilization is defined as Total ASU Capacity divided by Physical Storage Capacity.

<u>Clause 2.8.2</u>

Protected Application Utilization is defined as (Total ASU Capacity plus total Data Protection Capacity minus unused Data Protection Capacity) divided by Physical Storage Capacity.

<u>Clause 2.8.3</u>

Unused Storage Ratio is defined as Total Unused Capacity divided by Physical Storage Capacity and may not exceed 45%.

SPC-1 Storage Capacity Utilization				
Application Utilization	27.89%			
Protected Application Utilization	55.77%			
Unused Storage Ratio	30.96%			

Logical Volume Capacity and ASU Mapping

<u>Clause 9.4.3.6.3</u>

A table illustrating the capacity of each ASU and the mapping of Logical Volumes to ASUs shall be provided in the FDR. ... Logical Volumes shall be sequenced in the table from top to bottom per its position in the contiguous address space of each ASU. The capacity of each Logical Volume shall be stated. ... In conjunction with this table, the Test Sponsor shall provide a complete description of the type of data protection (see Clause 2.4.5) used on each Logical Volume.

Logical Volume Capacity and Mapping							
ASU-1 (2,705.829 GB)	ASU-2 (2,705.829 GB)	ASU-3 (612.127 GB)					
4 Logical Volumes 676.457 GB per Logical Volume (676.457 GB used per Logical Volume)	4 Logical Volumes 676.457 GB per Logical Volume (676.457 GB used per Logical Volume)	2 Logical Volumes 306.064 GB per Logical Volume (306.064 GB used per Logical Volume))					

The Data Protection Level used for all Logical Volumes was <u>Protected 2</u> using *Mirroring* as described on page <u>12</u>. See "ASU Configuration" in the <u>IOPS Test Results File</u> for more detailed configuration information.

SPC-1 BENCHMARK EXECUTION RESULTS

This portion of the Full Disclosure Report documents the results of the various SPC-1 Tests, Test Phases, and Test Runs. An <u>SPC-1 glossary</u> on page 61 contains definitions of terms specific to the SPC-1 Tests, Test Phases, and Test Runs.

<u>Clause 5.4.3</u>

The Tests must be executed in the following sequence: Primary Metrics, Repeatability, and Data Persistence. That required sequence must be uninterrupted from the start of Primary Metrics to the completion of Persistence Test Run 1. Uninterrupted means the Benchmark Configuration shall not be power cycled, restarted, disturbed, altered, or adjusted during the above measurement sequence. If the required sequence is interrupted other than for the Host System/TSC power cycle between the two Persistence Test Runs, the measurement is invalid.

SPC-1 Tests, Test Phases, and Test Runs

The SPC-1 benchmark consists of the following Tests, Test Phases, and Test Runs:

- Primary Metrics Test
 - > Sustainability Test Phase and Test Run
 - > IOPS Test Phase and Test Run
 - > Response Time Ramp Test Phase
 - 95% of IOPS Test Run
 - 90% of IOPS Test Run
 - $_{\circ}$ ~~ 80% of IOPS Test Run
 - $_{\circ}$ ~50% of IOPS Test Run
 - 10% of IOPS Test Run (LRT)

• Repeatability Test

- > Repeatability Test Phase 1
 - 10% of IOPS Test Run (LRT)
 - IOPS Test Run
- > Repeatability Test Phase 2
 - 10% of IOPS Test Run (LRT)
 - IOPS Test Run
- Data Persistence Test
 - > Data Persistence Test Run 1
 - > Data Persistence Test Run 2

Each Test is an atomic unit that must be executed from start to finish before any other Test, Test Phase, or Test Run may be executed.

The results from each Test, Test Phase, and Test Run are listed below along with a more detailed explanation of each component.

"Ramp-Up" Test Runs

<u>Clause 5.3.13</u>

In order to warm-up caches or perform the initial ASU data migration in a multi-tier configuration, a Test Sponsor may perform a series of "Ramp-Up" Test Runs as a substitute for an initial, gradual Ramp-Up.

Clause 5.3.13.3

The "Ramp-Up" Test Runs will immediately precede the Primary Metrics Test as part of the uninterrupted SPC-1 measurement sequence.

Clause 9.4.3.7.1

If a series of "Ramp-Up" Test Runs were included in the SPC-1 measurement sequence, the FDR shall report the duration (ramp-up and measurement interval), BSU level, SPC-1 IOPS and average response time for each "Ramp-Up" Test Run in an appropriate table.

There were no "Ramp-Up" Test Runs executed.

Primary Metrics Test - Sustainability Test Phase

Clause 5.4.4.1.1

The Sustainability Test Phase has exactly one Test Run and shall demonstrate the maximum sustainable I/O Request Throughput within at least a continuous eight (8) hour Measurement Interval. This Test Phase also serves to insure that the TSC has reached Steady State prior to reporting the final maximum I/O Request Throughput result (SPC-1 IOPSTM).

Clause 5.4.4.1.2

The computed I/O Request Throughput of the Sustainability Test must be within 5% of the reported SPC-1 $IOPS^{TM}$ result.

Clause 5.4.4.1.4

The Average Response Time, as defined in Clause 5.1.1, will be computed and reported for the Sustainability Test Run and cannot exceed 30 milliseconds. If the Average Response time exceeds that 30-milliseconds constraint, the measurement is invalid.

Clause 9.4.3.7.2

For the Sustainability Test Phase the FDR shall contain:

- 1. A Data Rate Distribution graph and data table.
- 2. I/O Request Throughput Distribution graph and data table.
- 3. A Response Time Frequency Distribution graph and table.
- 4. An Average Response Time Distribution graph and table.
- 5. The human readable Test Run Results File produced by the Workload Generator (may be included in an appendix).
- 6. A listing or screen image of all input parameters supplied to the Workload Generator (may be included in an appendix).
- 7. The Measured Intensity Multiplier for each I/O stream.
- 8. The variability of the Measured Intensity Multiplier, as defined in Clause 5.3.13.3.

SPC-1 Workload Generator Input Parameters

The SPC-1 Workload Generator input parameters for the Sustainability, IOPS, Response Time Ramp, Repeatability, and Persistence Test Runs are documented in <u>Appendix</u> <u>E: SPC-1 Workload Generator Input Parameters</u> on Page <u>82</u>.

Sustainability Test Results File

A link to the test results file generated from the Sustainability Test Run is listed below.

Sustainability Test Results File

Sustainability – Data Rate Distribution Data (MB/second)

The Sustainability Data Rate table of data is not embedded in this document due to its size. The table is available via the following URL:

Sustainability Data Rate Table

Sustainability – Data Rate Distribution Graph



Sustainability – I/O Request Throughput Distribution Data

The Sustainability I/O Request Throughput table of data is not embedded in this document due to its size. The table is available via the following URL:

Sustainability I/O Request Throughput Table

Sustainability – I/O Request Throughput Distribution Graph



Sustainability - Average Response Time (ms) Distribution Data

The Sustainability Average Response Time table of data is not embedded in this document due to its size. The table is available via the following URL:

Sustainability Average Response Time Table

Sustainability – Average Response Time (ms) Distribution Graph



Response Time (ms)	0-0.25	>0.25-0.5	>0.5-0.75	>0.75-1.0	>1.0-1.25	>1.25-1.5	>1.5-1.75	>1.75-2.0
Read	9,526,451	12,555,580	2,977,997	3,075,237	1,539,319	1,348,981	1,335,714	1,910,868
Write	106,054,850	214,166,723	22,456,006	27,415,993	9,728,165	9,456,070	4,967,169	5,210,323
All ASUs	115,581,301	226,722,303	25,434,003	30,491,230	11,267,484	10,805,051	6,302,883	7,121,191
ASU1	43,261,594	87,925,656	16,935,251	17,527,579	8,245,019	9,925,828	5,670,321	6,360,107
ASU2	10,728,221	18,495,162	1,861,315	2,411,542	851,831	777,354	608,146	721,194
ASU3	61,591,486	120,301,485	6,637,437	10,552,109	2,170,634	101,869	24,416	39,890
Response Time (ms)	>2.0-2.5	>2.5-3.0	>3.0-3.5	>3.5-4.0	>4.0-4.5	>4.5-5.0	>5.0-6.0	>6.0-7.0
Read	4,382,435	6,620,159	7,405,757	9,727,889	9,847,314	11,723,500	22,928,812	19,761,158
Write	8,451,898	5,522,387	4,579,776	3,036,867	2,576,560	1,736,598	2,595,737	1,677,060
All ASUs	12,834,333	12,142,546	11,985,533	12,764,756	12,423,874	13,460,098	25,524,549	21,438,218
ASU1	11,300,240	10,500,840	10,211,893	10,778,910	10,410,080	11,332,399	21,439,833	17,842,383
ASU2	1,418,036	1,618,165	1,696,384	1,967,867	1,951,653	2,113,779	4,017,153	3,535,080
ASU3	116,057	23,541	77,256	17,979	62,141	13,920	67,563	60,755
Response Time (ms)	>7.0-8.0	>8.0-9.0	>9.0-10.0	>10.0-15.0	>15.0-20.0	>20.0-25.0	>25.0-30.0	>30.0
Read	16,249,836	13,789,585	12,320,835	39,715,118	19,871,606	11,510,762	7,517,374	38,039,284
Write	1,175,649	884,120	694,619	2,677,231	1,642,127	561,667	321,973	1,069,557
All ASUs	17,425,485	14,673,705	13,015,454	42,392,349	21,513,733	12,072,429	7,839,347	39,108,841
ASU1	14,428,242	12,120,129	10,679,507	33,640,678	16,327,268	9,224,641	5,955,272	29,668,132
ASU2	2,941,514	2,500,603	2,284,848	8,005,910	4,529,149	2,792,487	1,872,999	9,402,561
ASU3	55,729	52,973	51,099	745,761	657,316	55,301	11,076	38,148

Sustainability - Response Time Frequency Distribution Data

Sustainability – Response Time Frequency Distribution Graph



SPC BENCHMARK 1[™] V1.14 Dell, Inc. Dell EqualLogic PS6210XV Array FULL DISCLOSURE REPORT

Sustainability – Measured Intensity Multiplier and Coefficient of Variation

<u>Clause 3.4.3</u>

IM – *Intensity Multiplier:* The ratio of I/Os for each I/O stream relative to the total I/Os for all I/O streams (ASU1-1 – ASU3-1) as required by the benchmark specification.

Clauses 5.1.10 and 5.3.15.2

MIM – **Measured Intensity Multiplier:** The Measured Intensity Multiplier represents the ratio of measured I/Os for each I/O stream relative to the total I/Os measured for all I/O streams (ASU1-1 – ASU3-1). This value may differ from the corresponding Expected Intensity Multiplier by no more than 5%.

Clause 5.3.15.3

COV – Coefficient of Variation: This measure of variation for the Measured Intensity Multiplier cannot exceed 0.2.

	ASU1-1	ASU1-2	ASU1-3	ASU1-4	ASU2-1	ASU2-2	ASU2-3	ASU3-1
ІМ	0.0350	0.2810	0.0700	0.2100	0.0180	0.0700	0.0350	0.2810
MIM	0.0350	02810	0.0700	0.210	0.0180	0.0700	0.0350	0.2810
COV	0.004	0.001	0.003	0.002	0.005	0.003	0.004	0.001

Primary Metrics Test – IOPS Test Phase

Clause 5.4.4.2

The IOPS Test Phase consists of one Test Run at the 100% load point with a Measurement Interval of ten (10) minutes. The IOPS Test Phase immediately follows the Sustainability Test Phase without any interruption or manual intervention.

The IOPS Test Run generates the SPC-1 IOPS[™] primary metric, which is computed as the I/O Request Throughput for the Measurement Interval of the IOPS Test Run.

The Average Response Time is computed for the IOPS Test Run and cannot exceed 30 milliseconds. If the Average Response Time exceeds the 30 millisecond constraint, the measurement is invalid.

Clause 9.4.3.7.3

For the IOPS Test Phase the FDR shall contain:

- 1. I/O Request Throughput Distribution (data and graph).
- 2. A Response Time Frequency Distribution.
- 3. An Average Response Time Distribution.
- 4. The human readable Test Run Results File produced by the Workload Generator.
- 5. A listing or screen image of all input parameters supplied to the Workload Generator.
- 6. The total number of I/O Requests completed in the Measurement Interval as well as the number of I/O Requests with a Response Time less than or equal to 30 milliseconds and the number of I/O Requests with a Response Time greater than 30 milliseconds.

SPC-1 Workload Generator Input Parameters

The SPC-1 Workload Generator input parameters for the Sustainability, IOPS, Response Time Ramp, Repeatability, and Persistence Test Runs are documented in <u>Appendix</u> <u>E: SPC-1 Workload Generator Input Parameters on Page 82</u>.

IOPS Test Results File

A link to the test results file generated from the IOPS Test Run is listed below.

IOPS Test Results File
503 BSUs	Start	Stop	Interval	Duration
Start-Up/Ramp-Up	1:13:17	1:16:18	0-2	0:03:01
Measurement Interval	1:16:18	1:26:18	3-12	0:10:00
60 second intervals	All ASUs	ASU1	ASU2	ASU3
0	25,178.98	15,006.45	3,093.73	7,078.80
1	25,087.87	14,943.23	3,093.72	7,050.92
2	25,142.48	14,983.97	3,095.80	7,062.72
3	25,138.53	14,968.78	3,104.17	7,065.58
4	25,177.03	15,022.97	3,086.97	7,067.10
5	25,169.65	15,001.67	3,099.37	7,068.62
6	25,170.72	14,990.43	3,096.02	7,084.27
7	25,130.52	14,985.48	3,091.02	7,054.02
8	25,147.25	14,991.75	3,090.67	7,064.83
9	25,126.17	14,966.72	3,090.25	7,069.20
10	25,115.85	14,969.10	3,093.48	7,053.27
11	25,141.72	14,980.67	3,102.85	7,058.20
12	25,154.78	14,993.77	3,094.23	7,066.78
Average	25,147.22	14,987.13	3,094.90	7,065.19

IOPS Test Run – I/O Request Throughput Distribution Data

IOPS Test Run - I/O Request Throughput Distribution Graph



SPC BENCHMARK 1[™] V1.14 Dell, Inc. Dell EqualLogic PS6210XV Array FULL DISCLOSURE REPORT

503 BSUs	Start	Stop	Interval	Duration
Start-Up/Ramp-Up	1:13:17	1:16:18	0-2	0:03:01
Measurement Interval	1:16:18	1:26:18	3-12	0:10:00
60 second intervals	All ASUs	ASU1	ASU2	ASU3
0	5.55	7.16	9.36	0.47
1	6.96	8.90	12.32	0.50
2	10.27	13.02	19.37	0.46
3	8.88	11.19	16.87	0.49
4	8.16	10.18	15.97	0.46
5	8.23	10.28	16.03	0.46
6	9.26	11.61	18.00	0.46
7	7.66	9.63	14.57	0.47
8	7.89	9.91	15.05	0.47
9	8.18	10.29	15.62	0.47
10	8.51	10.68	16.25	0.52
11	7.87	9.89	14.93	0.46
12	8.36	10.45	16.20	0.49
Average	8.30	10.41	15.95	0.48

IOPS Test Run – Average Response Time (ms) Distribution Data

IOPS Test Run - Average Response Time (ms) Distribution Graph



SPC BENCHMARK 1[™] V1.14 Dell, Inc. Dell EqualLogic PS6210XV Array FULL DISCLOSURE REPORT

Response Time (ms)	0-0.25	>0.25-0.5	>0.5-0.75	>0.75-1.0	>1.0-1.25	>1.25-1.5	>1.5-1.75	>1.75-2.0
Read	226,518	299,269	69,632	69,401	37,065	31,860	30,785	42,203
Write	2,178,246	4,528,998	466,020	534,020	204,793	194,347	102,478	105,722
All ASUs	2,404,764	4,828,267	535,652	603,421	241,858	226,207	133,263	147,925
ASU1	934,891	1,882,148	357,822	353,554	174,966	208,263	120,085	131,945
ASU2	218,778	395,295	39,433	47,516	18,439	15,806	12,693	15,048
ASU3	1,251,095	2,550,824	138,397	202,351	48,453	2,138	485	932
Response Time (ms)	>2.0-2.5	>2.5-3.0	>3.0-3.5	>3.5-4.0	>4.0-4.5	>4.5-5.0	>5.0-6.0	>6.0-7.0
Read	93,959	137,730	153,184	201,099	201,591	240,394	469,051	404,825
Write	174,838	114,062	95,041	63,566	54,772	36,106	54,916	35,461
All ASUs	268,797	251,792	248,225	264,665	256,363	276,500	523,967	440,286
ASU1	236,825	217,545	211,516	223,231	214,167	232,217	438,450	365,075
ASU2	29,432	33,773	35,219	41,028	40,921	44,020	84,085	73,891
ASU3	2,540	474	1,490	406	1,275	263	1,432	1,320
Response Time (ms)	>7.0-8.0	>8.0-9.0	>9.0-10.0	>10.0-15.0	>15.0-20.0	>20.0-25.0	>25.0-30.0	>30.0
Read	331,443	282,813	254,080	816,536	405,187	232,909	150,941	767,213
Write	25,157	18,951	14,627	58,431	36,280	12,039	6,643	22,809
All ASUs	356,600	301,764	268,707	874,967	441,467	244,948	157,584	790,022
ASU1	294,207	248,095	219,364	691,193	333,939	186,379	119,246	596,940
ASU2	61,092	52,574	48,237	168,071	93,820	57,429	38,110	192,130
ASU3	1,301	1,095	1,106	15,703	13,708	1,140	228	952

IOPS Test Run - Response Time Frequency Distribution Data

IOPS Test Run – Response Time Frequency Distribution Graph



SPC BENCHMARK 1[™] V1.14 Dell, Inc. Dell EqualLogic PS6210XV Array FULL DISCLOSURE REPORT

IOPS Test Run – I/O Request Information

I/O Requests Completed in the Measurement Interval	I/O Requests Completed with Response Time = or < 30 ms	I/O Requests Completed with Response Time > 30 ms	
15,088,011	14,29,989	790,022	

IOPS Test Run – Measured Intensity Multiplier and Coefficient of Variation

<u>Clause 3.4.3</u>

IM – *Intensity Multiplier:* The ratio of I/Os for each I/O stream relative to the total I/Os for all I/O streams (ASU1-1 – ASU3-1) as required by the benchmark specification.

Clauses 5.1.10 and 5.3.15.2

MIM – **Measured Intensity Multiplier:** The Measured Intensity Multiplier represents the ratio of measured I/Os for each I/O stream relative to the total I/Os measured for all I/O streams (ASU1-1 – ASU3-1). This value may differ from the corresponding Expected Intensity Multiplier by no more than 5%.

Clause 5.3.15.3

COV – Coefficient of Variation: This measure of variation for the Measured Intensity Multiplier cannot exceed 0.2.

	ASU1-1	ASU1-2	ASU1-3	ASU1-4	ASU2-1	ASU2-2	ASU2-3	ASU3-1
ІМ	0.0350	0.2810	0.0700	0.2100	0.0180	0.0700	0.0350	0.2810
MIM	0.0350	0.2811	0.0702	0.2097	0.0180	0.0701	0.0350	0.2810
COV	0.005	0.001	0.003	0.002	0.009	0.003	0.004	0.001

Primary Metrics Test – Response Time Ramp Test Phase

<u>Clause 5.4.4.3</u>

The Response Time Ramp Test Phase consists of five Test Runs, one each at 95%, 90%, 80%, 50%, and 10% of the load point (100%) used to generate the SPC-1 IOPSTM primary metric. Each of the five Test Runs has a Measurement Interval of ten (10) minutes. The Response Time Ramp Test Phase immediately follows the IOPS Test Phase without any interruption or manual intervention.

The five Response Time Ramp Test Runs, in conjunction with the IOPS Test Run (100%), demonstrate the relationship between Average Response Time and I/O Request Throughput for the Tested Storage Configuration (TSC) as illustrated in the response time/throughput curve on page 16.

In addition, the Average Response Time measured during the 10% Test Run is the value for the SPC-1 LRTTM metric. That value represents the Average Response Time of a lightly loaded TSC.

Clause 9.4.3.7.4

The following content shall appear in the FDR for the Response Time Ramp Phase:

- 1. A Response Time Ramp Distribution.
- 2. The human readable Test Run Results File produced by the Workload Generator for each Test Run within the Response Time Ramp Test Phase.
- 3. For the 10% Load Level Test Run (SPC-1 LRT[™] metric) an Average Response Time Distribution.
- 4. A listing or screen image of all input parameters supplied to the Workload Generator.

SPC-1 Workload Generator Input Parameters

The SPC-1 Workload Generator input parameters for the Sustainability, IOPS, Response Time Ramp, Repeatability, and Persistence Test Runs are documented in <u>Appendix</u> <u>E: SPC-1 Workload Generator Input Parameters</u> on Page <u>82</u>.

Response Time Ramp Test Results File

A link to each test result file generated from each Response Time Ramp Test Run list listed below.

95% Load Level 90% Load Level 80% Load Level

50% Load Level

10% Load Level

Response Time Ramp Distribution (IOPS) Data

The five Test Runs that comprise the Response Time Ramp Phase are executed at 95%, 90%, 80%, 50%, and 10% of the Business Scaling Unit (BSU) load level used to produce the SPC-1 IOPSTM primary metric. The 100% BSU load level is included in the following Response Time Ramp data table and graph for completeness.

100% Load Level:					95% Load Level:				
503 BSUs	Start	Stop	Interval	Duration	477 BSUs	Start	Stop	Interval	Duration
Start-Up/Ramp-Up	1:13:17	1:16:18	0-3	0:03:01	Start-Up/Ramp-Up	1:26:22	1:29:23	0-3	0:03:01
Measurement Interval	1:16:18	1:26:18	3-12	0:10:00	Measurement Interval	1:29:23	1:39:23	3-12	0:10:00
(60 second intervals)	All ASUs	ASU-1	ASU-2	ASU-3	(60 second intervals)	All ASUs	ASU-1	ASU-2	ASU-3
Minutes of Test Run	All ASUs	ASU1	ASU2	ASU3	Minutes of Test Run	All ASUs	ASU1	ASU2	ASU3
0	25,178.98	15,006.45	3,093.73	7,078.80	0	23,836.88	14,207.97	2,936.82	6,692.10
1	25,087.87	14,943.23	3,093.72	7,050.92	1	23,862.48	14,227.92	2,926.35	6,708.22
2	25,142.48	14,983.97	3,095.80	7,062.72	2	23,868.08	14,211.32	2,932.72	6,724.05
3	25,138.53	14,968.78	3,104.17	7,065.58	3	23,809.80	14,194.43	2,923.52	6,691.85
4	25,177.03	15,022.97	3,086.97	7,067.10	4	23,873.48	14,225.30	2,928.33	6,719.85
5	25,169.65	15,001.67	3,099.37	7,068.62	5	23,858.43	14,230.70	2,918.18	6,709.55
6	25,170.72	14,990.43	3,096.02	7,084.27	6	23,864.83	14,221.27	2,938.63	6,704.93
7	25,130.52	14,985.48	3,091.02	7,054.02	7	23,828.50	14,197.12	2,925.33	6,706.05
8	25,147.25	14,991.75	3,090.67	7,064.83	8	23,856.13	14,225.10	2,933.30	6,697.73
9	25,126.17	14,966.72	3,090.25	7,069.20	9	23,814.88	14,190.87	2,932.08	6,691.93
10	25,115.85	14,969.10	3,093.48	7,053.27	10	23,870.52	14,233.50	2,937.15	6,699.87
11	25,141.72	14,980.67	3,102.85	7,058.20	11	23,855.82	14,221.80	2,927.87	6,706.15
12	25, 154, 78	14,993,77	3.094.23	7.066.78	12	23 844 02	14 192 58	2,939,43	6.712.00
		,	0,00	.,	12	20,011.02	14,102.00	_,	0,1 12100
90% Load Level: 452 BSUs	Start	Stop	Interval	Duration	80% Load Level: 402 BSUs	Start	Stop	Interval	Duration
90% Load Level: 452 BSUs Start-Up/Ramp-Up	Start 1:39:27	Stop 1:42:28	Interval	Duration 0:03:01	80% Load Level: 402 BSUs Start-Up/Ramp-Up	Start 1:52:32	Stop 1:55:33	Interval	Duration 0:03:01
90% Load Level: 452 BSUs Start-Up/Ramp-Up Measurement Interval	Start 1:39:27 1:42:28	Stop 1:42:28 1:52:28	Interval 0-3 3-12	Duration 0:03:01 0:10:00	80% Load Level: 402 BSUs Start-Up/Ramp-Up Measurement Interval	Start 1:52:32 1:55:33	Stop 1:55:33 2:05:33	Interval 0-3 3-12	Duration 0:03:01 0:10:00
90% Load Level: 452 BSUs Start-Up/Ramp-Up Measurement Interval (60 second intervals)	Start 1:39:27 1:42:28 All ASUs	Stop 1:42:28 1:52:28 ASU-1	Interval 0-3 3-12 ASU-2	Duration 0:03:01 0:10:00 ASU-3	80% Load Level: 402 BSUs Start-Up/Ramp-Up Measurement Interval (60 second intervals)	Start 1:52:32 1:55:33 All ASUs	Stop 1:55:33 2:05:33 ASU-1	Interval 0-3 3-12 ASU-2	Duration 0:03:01 0:10:00 ASU-3
90% Load Level: 452 BSUs Start-Up/Ramp-Up Measurement Interval (60 second intervals) Minutes of Test Run	Start 1:39:27 1:42:28 All ASUs	Stop 1:42:28 1:52:28 ASU-1 ASU1	Interval 0-3 3-12 ASU-2	Duration 0:03:01 0:10:00 ASU-3 ASU3	80% Load Level: 402 BSUs Start-Up/Ramp-Up Measurement Interval (60 second intervals) Minutes of Test Run	Start 1:52:32 1:55:33 All ASUs	Stop 1:55:33 2:05:33 ASU-1 ASU1	Interval 0-3 3-12 ASU-2 ASU2	Duration 0:03:01 0:10:00 ASU-3 ASU3
90% Load Level: 452 BSUs Start-Up/Ramp-Up Measurement Interval (60 second intervals) Minutes of Test Run 0	Start 1:39:27 1:42:28 All ASUs All ASUs 22,610.15	Stop 1:42:28 1:52:28 ASU-1 ASU1 13,473.92	Interval 0-3 3-12 ASU-2 ASU2 2,777.02	Duration 0:03:01 0:10:00 ASU-3 ASU3 6,359.22	80% Load Level: 402 BSUs Start-Up/Ramp-Up Measurement Interval (60 second intervals) Minutes of Test Run 0	Start 1:52:32 1:55:33 All ASUs All ASUs 20,077.97	Stop 1:55:33 2:05:33 ASU-1 ASU1 11,977.42	Interval 0-3 3-12 ASU-2 ASU2 2,464.83	Duration 0:03:01 0:10:00 ASU-3 ASU3 5,635.72
90% Load Level: 452 BSUs Start-Up/Ramp-Up Measurement Interval (60 second intervals) Minutes of Test Run 0 1	Start 1:39:27 1:42:28 All ASUs 22,610.15 22,609.38	Stop 1:42:28 1:52:28 ASU-1 ASU1 13,473.92 13,472.02	Interval 0-3 3-12 ASU-2 ASU2 2,777.02 2,775.73	Duration 0:03:01 0:10:00 ASU-3 ASU3 6,359.22 6,361.63	80% Load Level: 402 BSUs Start-Up/Ramp-Up Measurement Interval (60 second intervals) Minutes of Test Run 0 1	Start 1:52:32 1:55:33 All ASUs All ASUs 20,077.97 20,093.98	Stop 1:55:33 2:05:33 ASU-1 ASU1 11,977.42 11,979.68	Interval 0-3 3-12 ASU-2 ASU2 2,464.83 2,469.47	Duration 0:03:01 0:10:00 ASU-3 ASU3 5,635.72 5,644.83
90% Load Level: 452 BSUs Start-Up/Ramp-Up Measurement Interval (60 second intervals) Minutes of Test Run 0 1 2	Start 1:39:27 1:42:28 All ASUs 22,610.15 22,609.38 22,583.53	Stop 1:42:28 1:52:28 ASU-1 ASU1 13,473.92 13,472.02 13,460.20	Interval 0-3 3-12 ASU2 2,777.02 2,775.73 2,773.87	Duration 0:03:01 0:10:00 ASU-3 ASU3 6,359.22 6,361.63 6,349.47	80% Load Level: 402 BSUs Start-Up/Ramp-Up Measurement Interval (60 second intervals) Minutes of Test Run 0 1	Start 1:52:32 1:55:33 All ASUs 20,077.97 20,093.98 20,115.42	Stop 1:55:33 2:05:33 ASU-1 ASU1 11,977.42 11,978.95	Interval 0-3 3-12 ASU-2 ASU-2 2,464.83 2,469.47 2,479.63	Duration 0:03:01 0:10:00 ASU-3 ASU3 5,635.72 5,644.83 5,656.83
90% Load Level: 452 BSUs Start-Up/Ramp-Up Measurement Interval (60 second intervals) Minutes of Test Run 0 1 2 3	Start 1:39:27 1:42:28 All ASUs 22,610.15 22,609.38 22,583.53 22,600.62	Stop 1:42:28 1:52:28 ASU-1 ASU1 13,473.92 13,472.02 13,460.20 13,472.55	Interval 0-3 3-12 ASU-2 ASU2 2,777.02 2,775.73 2,773.87 2,776.32	Duration 0:03:01 0:10:00 ASU3 6,359.22 6,361.63 6,349.47 6,351.75	80% Load Level: 402 BSUs Start-Up/Ramp-Up Measurement Interval (60 second intervals) Minutes of Test Run 0 1 2 3	Start 1:52:32 1:55:33 All ASUs 20,077.97 20,093.98 20,115.42 20,097.90	Stop 1:55:33 2:05:33 ASU-1 ASU1 11,977.42 11,979.68 11,978.95 11,971.95	Interval 0-3 3-12 ASU-2 ASU2 2,464.83 2,469.47 2,479.63 2,467.53	Duration 0:03:01 0:10:00 ASU-3 5,635.72 5,644.83 5,656.83 5,658.42
90% Load Level: 452 BSUs Start-Up/Ramp-Up Measurement Interval (60 second intervals) Minutes of Test Run 0 1 2 3 4	Start 1:39:27 1:42:28 All ASUs 22,610.15 22,609.38 22,583.53 22,600.62 22,609.13	Stop 1:42:28 1:52:28 ASU-1 ASU1 13,473.92 13,472.02 13,460.20 13,472.55 13,463.47	Interval 0-3 3-12 ASU-2 ASU2 2,777.02 2,775.73 2,773.87 2,776.32 2,785.25	Duration 0:03:01 0:10:00 ASU3 6,359.22 6,361.63 6,349.47 6,351.75 6,360.42	80% Load Level: 402 BSUs Start-Up/Ramp-Up Measurement Interval (60 second intervals) Minutes of Test Run 0 1 2 3 4	Start 1:52:32 1:55:33 All ASUs 20,077.97 20,093.98 20,115.42 20,097.90 20,127.10	Stop 1:55:33 2:05:33 ASU-1 ASU1 11,977.42 11,979.68 11,978.95 11,971.95 11,984.57	Interval 0-3 3-12 ASU-2 ASU2 2,464.83 2,469.47 2,479.63 2,467.53 2,485.18	Duration 0:03:01 0:10:00 ASU-3 5,635.72 5,644.83 5,656.83 5,658.42 5,657.35
90% Load Level: 452 BSUs Start-Up/Ramp-Up Measurement Interval (60 second intervals) Minutes of Test Run 0 1 2 3 4 5	Start 1:39:27 1:42:28 All ASUs 22,610.15 22,609.38 22,583.53 22,600.62 22,609.13 22,609.57	Stop 1:42:28 1:52:28 ASU-1 ASU1 13,473.92 13,472.02 13,460.20 13,472.55 13,463.47 13,469.08	Interval 0-3 3-12 ASU2 2,777.02 2,775.73 2,773.87 2,776.32 2,785.25 2,775.83	Duration 0:03:01 0:10:00 ASU3 6,359.22 6,361.63 6,349.47 6,351.75 6,360.42 6,364.65	80% Load Level: 402 BSUs Start-Up/Ramp-Up Measurement Interval (60 second intervals) Minutes of Test Run 0 1 2 3 4 5	Start 1:52:32 1:55:33 All ASUs 20,077.97 20,093.98 20,115.42 20,097.90 20,127.10 20,104.33	Stop 1:55:33 2:05:33 ASU-1 ASU1 11,977.42 11,979.68 11,978.95 11,971.95 11,984.57 11,996.50	Interval 0-3 3-12 ASU-2 ASU-2 2,464.83 2,469.47 2,479.63 2,467.53 2,485.18 2,466.87	Duration 0:03:01 0:10:00 ASU3 5,635.72 5,644.83 5,656.83 5,658.42 5,657.35 5,640.97
90% Load Level: 452 BSUs Start-Up/Ramp-Up Measurement Interval (60 second intervals) Minutes of Test Run 0 1 2 3 4 5 6	Start 1:39:27 1:42:28 All ASUs 22,610.15 22,609.38 22,583.53 22,600.62 22,609.13 22,609.57 22,594.20	Stop 1:42:28 1:52:28 ASU-1 ASU1 13,473.92 13,472.02 13,460.20 13,472.55 13,463.47 13,463.47 13,463.92	Interval 0-3 3-12 ASU-2 ASU2 2,777.02 2,775.73 2,776.32 2,785.25 2,775.83 2,779.35	Duration 0:03:01 0:10:00 ASU3 6,359.22 6,361.63 6,349.47 6,351.75 6,360.42 6,364.65 6,350.93	80% Load Level: 402 BSUs Start-Up/Ramp-Up Measurement Interval (60 second intervals) Minutes of Test Run 0 1 2 3 4 5 6	Start 1:52:32 1:55:33 All ASUs 20,077.97 20,093.98 20,115.42 20,097.90 20,127.10 20,118.73	Stop 1:55:33 2:05:33 ASU-1 ASU1 11,977.42 11,979.68 11,978.95 11,971.95 11,984.57 11,996.50 11,987.85	Interval 0-3 3-12 ASU2 2,464.83 2,469.47 2,479.63 2,467.53 2,485.18 2,466.87 2,473.92	Duration 0:03:01 0:10:00 ASU3 5,635.72 5,644.83 5,656.83 5,657.35 5,640.97 5,656.97
90% Load Level: 452 BSUs Start-Up/Ramp-Up Measurement Interval (60 second intervals) Minutes of Test Run 0 1 2 3 4 5 6 7	Start 1:39:27 1:42:28 All ASUs 22,610.15 22,609.38 22,583.53 22,600.62 22,609.13 22,609.57 22,594.20 22,581.30	Stop 1:42:28 1:52:28 ASU-1 ASU1 13,473.92 13,472.02 13,460.20 13,472.55 13,463.47 13,463.47 13,463.82 13,463.82	Interval 0-3 3-12 ASU-2 ASU2 2,777.02 2,775.73 2,776.32 2,785.25 2,775.83 2,779.35 2,773.87	Duration 0:03:01 0:10:00 ASU3 6,359.22 6,361.63 6,349.47 6,351.75 6,360.42 6,350.93 6,341.25	80% Load Level: 402 BSUs Start-Up/Ramp-Up Measurement Interval (60 second intervals) Minutes of Test Run 0 1 2 3 4 5 6 7	Start 1:52:32 1:55:33 All ASUs 20,077.97 20,093.98 20,115.42 20,097.90 20,127.10 20,104.33 20,118.73 20,092.08	Stop 1:55:33 2:05:33 ASU-1 ASU1 11,977.42 11,979.68 11,978.95 11,971.95 11,984.57 11,996.50 11,968.57	Interval 0-3 3-12 ASU2 2,464.83 2,469.47 2,479.63 2,467.53 2,485.18 2,466.87 2,473.92 2,466.95	Duration 0:03:01 0:10:00 ASU3 5,635.72 5,644.83 5,656.83 5,657.35 5,640.97 5,656.97 5,656.57
90% Load Level: 452 BSUs Start-Up/Ramp-Up Measurement Interval (60 second intervals) Minutes of Test Run 0 1 2 3 4 5 6 7 8	Start 1:39:27 1:42:28 All ASUs 22,610.15 22,609.38 22,583.53 22,609.13 22,609.57 22,581.30 22,576.53	Stop 1:42:28 1:52:28 ASU1 13,473.92 13,472.02 13,460.20 13,472.55 13,463.47 13,463.92 13,463.92 13,466.18 13,456.45	Interval 0-3 3-12 ASU2 2,777.02 2,775.73 2,773.87 2,776.32 2,785.25 2,775.83 2,775.83 2,773.87 2,773.87 2,773.87 2,774.05	Duration 0:03:01 0:10:00 ASU3 6,359.22 6,361.63 6,349.47 6,351.75 6,360.42 6,350.93 6,341.25 6,346.03	80% Load Level: 402 BSUs Start-Up/Ramp-Up Measurement Interval (60 second intervals) Minutes of Test Run 0 1 2 3 4 5 6 7 8	Start 1:52:32 1:55:33 All ASUs 20,077.97 20,093.98 20,115.42 20,097.90 20,127.10 20,148.73 20,092.08 20,090.37	Stop 1:55:33 2:05:33 ASU-1 ASU1 11,977.42 11,979.68 11,978.95 11,971.95 11,984.57 11,996.50 11,987.85 11,968.57 11,987.43	Interval 0-3 3-12 ASU-2 ASU2 2,464.83 2,469.47 2,479.63 2,467.53 2,485.18 2,466.87 2,473.92 2,466.95 2,465.78	Duration 0:03:01 0:10:00 ASU3 5,635.72 5,644.83 5,656.83 5,657.35 5,640.97 5,656.57 5,656.57 5,656.57 5,657.35
90% Load Level: 452 BSUs Start-Up/Ramp-Up Measurement Interval (60 second intervals) Minutes of Test Run 0 1 2 3 4 5 6 6 7 8 9	Start 1:39:27 1:42:28 All ASUs 22,610.15 22,609.38 22,583.53 22,609.13 22,609.57 22,581.30 22,576.53 22,592.17	Stop 1:42:28 1:52:28 ASU1 13,473.92 13,472.02 13,460.20 13,472.55 13,463.47 13,463.92 13,466.18 13,456.45 13,459.52	Interval 0-3 3-12 ASU2 2,777.02 2,775.73 2,773.87 2,776.32 2,785.25 2,775.83 2,775.83 2,773.87 2,773.87 2,774.05 2,769.02	Duration 0:03:01 0:10:00 ASU3 6,359.22 6,361.63 6,349.47 6,351.75 6,360.42 6,350.93 6,341.25 6,363.63	80% Load Level: 402 BSUs Start-Up/Ramp-Up Measurement Interval (60 second intervals) Minutes of Test Run 0 1 2 3 4 5 6 7 8 9	Start 1:52:32 1:55:33 All ASUs 20,077.97 20,093.98 20,115.42 20,097.90 20,127.10 20,148.73 20,092.08 20,090.37 20,088.32	Stop 1:55:33 2:05:33 ASU-1 ASU1 11,977.42 11,979.68 11,978.95 11,971.95 11,984.57 11,996.50 11,987.85 11,968.57 11,987.43 11,979.23	Interval 0-3 3-12 ASU2 2,464.83 2,469.47 2,479.63 2,467.53 2,485.18 2,466.87 2,473.92 2,466.95 2,465.78 2,471.75	Duration 0:03:01 0:10:00 ASU3 5,635.72 5,644.83 5,656.83 5,657.35 5,640.97 5,656.57 5,656.57 5,656.57 5,657.35 5,656.57 5,656.57 5,657.35
90% Load Level: 452 BSUs Start-Up/Ramp-Up Measurement Interval (60 second intervals) Minutes of Test Run 0 1 2 3 4 5 6 6 7 8 9 10	Start 1:39:27 1:42:28 All ASUs 22,610.15 22,609.38 22,583.53 22,609.13 22,609.57 22,584.30 22,576.53 22,592.17 22,596.82	Stop 1:42:28 1:52:28 ASU1 13,473.92 13,473.92 13,472.02 13,460.20 13,472.55 13,463.47 13,463.92 13,466.18 13,456.45 13,459.52 13,472.38	Interval 0-3 3-12 ASU2 2,777.02 2,775.73 2,773.87 2,776.32 2,785.25 2,775.83 2,775.83 2,779.35 2,773.87 2,774.05 2,769.02 2,779.67	Duration 0:03:01 0:10:00 ASU3 6,359.22 6,361.63 6,349.47 6,351.75 6,360.42 6,350.93 6,341.25 6,363.63 6,344.77	80% Load Level: 402 BSUs Start-Up/Ramp-Up Measurement Interval (60 second intervals) Minutes of Test Run 0 1 2 3 4 5 6 7 8 9 10	Start 1:52:32 1:55:33 All ASUs 20,077.97 20,093.98 20,115.42 20,097.90 20,127.10 20,148.73 20,092.08 20,090.37 20,093.33	Stop 1:55:33 2:05:33 ASU-1 ASU1 11,977.42 11,979.68 11,978.95 11,971.95 11,984.57 11,996.50 11,987.85 11,968.57 11,987.43 11,972.23 11,972.58	Interval 0-3 3-12 ASU2 2,464.83 2,469.47 2,479.63 2,467.53 2,485.18 2,466.87 2,473.92 2,466.95 2,465.78 2,471.75 2,483.82	Duration 0:03:01 0:10:00 ASU3 5,635.72 5,644.83 5,656.83 5,657.35 5,640.97 5,656.57 5,656.57 5,656.57 5,656.57 5,656.37 5,656.37 5,656.37 5,656.37 5,656.37 5,637.33 5,636.93
90% Load Level: 452 BSUs Start-Up/Ramp-Up Measurement Interval (60 second intervals) Minutes of Test Run 0 1 2 3 4 4 5 6 6 7 8 9 10 11	Start 1:39:27 1:42:28 All ASUs 22,610.15 22,609.38 22,583.53 22,609.13 22,609.57 22,581.30 22,576.53 22,592.17 22,570.82 22,570.82 22,570.82 22,570.82 22,570.82 22,570.82 22,570.82 22,570.82 22,570.82 22,570.82 22,570.82 22,570.82 22,570.82	Stop 1:42:28 1:52:28 ASU1 13,473.92 13,473.92 13,472.02 13,460.20 13,472.55 13,463.47 13,463.92 13,466.18 13,456.45 13,459.52 13,459.52 13,459.22	Interval 0-3 3-12 ASU2 2,777.02 2,775.73 2,773.87 2,776.32 2,785.25 2,775.83 2,775.83 2,779.35 2,773.87 2,774.05 2,769.02 2,775.43 2,775.43 2,775.43 2,775.43 2,775.43 2,775.43 2,775.43 2,775.43 2,775.43 2,775.43 2,775.43 2,775.43 2,775.43 2,775.43 2,775.43 2,775.43 2,775.45	Duration 0:03:01 0:10:00 ASU3 6,359.22 6,361.63 6,349.47 6,351.75 6,360.42 6,350.93 6,341.25 6,363.63 6,344.77 6,363.63 6,344.77	80% Load Level: 402 BSUs Start-Up/Ramp-Up Measurement Interval (60 second intervals) Minutes of Test Run 0 1 2 3 4 5 6 7 8 9 10 11	Start 1:52:32 1:55:33 All ASUs 20,077.97 20,093.98 20,115.42 20,097.90 20,127.10 20,148.73 20,092.08 20,093.33 20,093.33 20,093.33 20,093.33 20,093.33 20,090.50	Stop 1:55:33 2:05:33 ASU-1 ASU1 11,977.42 11,979.68 11,978.95 11,971.95 11,984.57 11,996.50 11,987.85 11,968.57 11,972.33 11,972.58 11,964.50	Interval 0-3 3-12 ASU2 2,464.83 2,469.47 2,479.63 2,467.53 2,485.18 2,466.87 2,473.92 2,466.95 2,465.78 2,471.75 2,483.82 2,468.35 2,465.78 2,471.75 2,483.82 2,468.35	Duration 0:03:01 0:10:00 ASU3 5,635.72 5,644.83 5,656.83 5,657.35 5,640.97 5,656.57 5,656.57 5,657.33 5,656.33 5,656.37 5,656.37 5,656.37 5,657.33 5,657.33 5,657.63

E0% Lood Loval									
50% Load Level:					10% Load Level:				
251 BSUs	Start	Stop	Interval	Duration	50 BSUs	Start	Stop	Interval	Duration
Start-Up/Ramp-Up	2:05:37	2:08:38	0-3	0:03:01	Start-Up/Ramp-Up	2:18:41	2:21:42	0-3	0:03:01
Measurement Interval	2:08:38	2:18:38	3-12	0:10:00	Measurement Interval	2:21:42	2:31:42	3-12	0:10:00
(60 second intervals)	All ASUs	ASU-1	ASU-2	ASU-3	(60 second intervals)	All ASUs	ASU-1	ASU-2	ASU-3
Minutes of Test Run	All ASUs	ASU1	ASU2	ASU3	Minutes of Test Run	All ASUs	ASU1	ASU2	ASU3
0	12,543.77	7,468.63	1,540.85	3,534.28	0	2,501.52	1,491.20	307.93	702.38
1	12,539.60	7,477.18	1,540.65	3,521.77	1	2,502.58	1,494.08	308.83	699.67
2	12,584.85	7,502.93	1,540.20	3,541.72	2	2,508.70	1,500.02	305.53	703.15
3	12,531.47	7,468.82	1,538.83	3,523.82	3	2,505.32	1,493.37	309.25	702.70
4	12,555.78	7,486.77	1,540.28	3,528.73	4	2,492.85	1,480.47	307.90	704.48
5	12,556.78	7,489.70	1,538.35	3,528.73	5	2,510.17	1,498.72	309.17	702.28
6	12,556.15	7,472.73	1,546.20	3,537.22	6	2,505.63	1,493.70	309.30	702.63
7	12,571.08	7,492.13	1,551.18	3,527.77	7	2,500.13	1,488.13	307.98	704.02
8	12,545.78	7,480.67	1,551.52	3,513.60	8	2,500.68	1,489.85	303.57	707.27
9	12,546.17	7,472.97	1,547.22	3,525.98	9	2,505.42	1,486.58	309.68	709.15
10	12,561.28	7,494.27	1,546.30	3,520.72	10	2,503.90	1,495.58	306.93	701.38
11	12,563.20	7,491.93	1,538.33	3,532.93	11	2,494.77	1,483.02	308.18	703.57
12	12,569.20	7,477.45	1,552.42	3,539.33	12	2,492.78	1,485.47	304.43	702.88

Response Time Ramp Distribution (IOPS) Data (continued)

Response Time Ramp Distribution (IOPS) Graph



FULL DISCLOSURE REPORT

50 BSUs	Start	Stop	Interval	Duration
Start-Up/Ramp-Up	2:18:41	2:21:42	0-2	0:03:01
Measurement Interval	2:21:42	2:31:42	3-12	0:10:00
60 second intervals	All ASUs	ASU1	ASU2	ASU3
0	2.41	3.28	2.49	0.54
1	2.23	3.02	2.30	0.51
2	2.26	3.03	2.49	0.52
3	2.38	3.23	2.51	0.51
4	2.20	2.96	2.39	0.53
5	2.21	3.00	2.30	0.50
6	2.26	3.01	2.55	0.52
7	2.30	3.12	2.39	0.52
8	2.16	2.90	2.29	0.55
9	2.18	2.95	2.32	0.48
10	2.25	3.04	2.36	0.53
11	2.31	3.14	2.37	0.54
12	2.23	3.00	2.43	0.51
Average	2.25	3.03	2.39	0.52

SPC-1 LRT[™] Average Response Time (ms) Distribution Data

SPC-1 LRT[™] Average Response Time (ms) Distribution Graph



SPC BENCHMARK 1[™] V1.14 Dell, Inc. Dell EqualLogic PS6210XV Array $FULL \, DISCLOSURE \, REPORT$

SPC-1 LRT[™] (10%) – Measured Intensity Multiplier and Coefficient of Variation

<u>Clause 3.4.3</u>

IM – *Intensity Multiplier:* The ratio of I/Os for each I/O stream relative to the total I/Os for all I/O streams (ASU1-1 – ASU3-1) as required by the benchmark specification.

<u>Clauses 5.1.10 and 5.3.15.2</u>

MIM – Measured Intensity Multiplier: The Measured Intensity Multiplier represents the ratio of measured I/Os for each I/O stream relative to the total I/Os measured for all I/O streams (ASU1-1 – ASU3-1). This value may differ from the corresponding Expected Intensity Multiplier by no more than 5%.

Clause 5.3.15.3

COV – Coefficient of Variation: This measure of variation for the Measured Intensity Multiplier cannot exceed 0.2.

	ASU1-1	ASU1-2	ASU1-3	ASU1-4	ASU2-1	ASU2-2	ASU2-3	ASU3-1
ІМ	0.0350	0.2810	0.0700	0.2100	0.0180	0.0700	0.0350	0.2810
MIM	0.0351	0.2810	0.0697	0.2097	0.0180	0.0700	0.0351	0.2815
COV	0.012	0.003	0.009	0.004	0.018	0.009	0.014	0.004

Repeatability Test

<u>Clause 5.4.5</u>

The Repeatability Test demonstrates the repeatability and reproducibility of the SPC-1 IOPS[™] primary metric and the SPC-1 LRT[™] metric generated in earlier Test Runs.

There are two identical Repeatability Test Phases. Each Test Phase contains two Test Runs. Each of the Test Runs will have a Measurement Interval of no less than ten (10) minutes. The two Test Runs in each Test Phase will be executed without interruption or any type of manual intervention.

The first Test Run in each Test Phase is executed at the 10% load point. The Average Response Time from each of the Test Runs is compared to the SPC-1 LRT^{TM} metric. Each Average Response Time value must be less than the SPC-1 LRT^{TM} metric plus 5% or less than the SPC-1 LRT^{TM} metric plus one (1) millisecond (ms).

The second Test Run in each Test Phase is executed at the 100% load point. The I/O Request Throughput from the Test Runs is compared to the SPC-1 IOPSTM primary metric. Each I/O Request Throughput value must be greater than the SPC-1 IOPSTM primary metric minus 5%. In addition, the Average Response Time for each Test Run cannot exceed 30 milliseconds.

If any of the above constraints are not met, the benchmark measurement is invalid.

Clause 9.4.3.7.5

The following content shall appear in the FDR for each Test Run in the two Repeatability Test Phases:

- 1. A table containing the results of the Repeatability Test.
- 2. An I/O Request Throughput Distribution graph and table.
- 3. An Average Response Time Distribution graph and table.
- 4. The human readable Test Run Results File produced by the Workload Generator.
- 5. A listing or screen image of all input parameters supplied to the Workload Generator.

SPC-1 Workload Generator Input Parameters

The SPC-1 Workload Generator input parameters for the Sustainability, IOPS, Response Time Ramp, Repeatability, and Persistence Test Runs are documented in <u>Appendix</u> <u>E: SPC-1 Workload Generator Input Parameters on Page 82</u>.

Repeatability Test Results File

The values for the SPC-1 IOPSTM, SPC-1 LRTTM, and the Repeatability Test measurements are listed in the tables below.

	SPC-1 IOPS™
Primary Metrics	25,147.22
Repeatability Test Phase 1	25,147.56
Repeatability Test Phase 2	25,166.77

The SPC-1 IOPS[™] values in the above table were generated using 100% of the specified Business Scaling Unit (BSU) load level. Each of the Repeatability Test Phase values for SPC-1 IOPS[™] must greater than 95% of the reported SPC-1 IOPS[™] Primary Metric.

	SPC-1 LRT™
Primary Metrics	2.25 ms
Repeatability Test Phase 1	2.21 ms
Repeatability Test Phase 2	2.20 ms

The average response time values in the SPC-1 LRT[™] column were generated using 10% of the specified Business Scaling Unit (BSU) load level. Each of the Repeatability Test Phase values for SPC-1 LRT[™] must be less than 105% of the reported SPC-1 LRT[™] Primary Metric or less than the reported SPC-1 LRT[™] Primary Metric plus one (1) millisecond (ms).

A link to the test result file generated from each Repeatability Test Run is listed below.

Repeatability Test Phase 1, Test Run 1 (LRT) Repeatability Test Phase 1, Test Run 2 (IOPS) Repeatability Test Phase 2, Test Run 1 (LRT) Repeatability Test Phase 2, Test Run 2 (IOPS)

50 BSUs	Start	Stop	Interval	Duration
Start-Up/Ramp-Up	2:31:50	2:34:50	0-2	0:03:00
Measurement Interval	2:34:50	2:44:50	3-12	0:10:00
60 second intervals	All ASUs	ASU1	ASU2	ASU3
0	2,487.68	1,487.00	308.55	692.13
1	2,496.15	1,481.93	310.67	703.55
2	2,505.43	1,494.30	309.03	702.10
3	2,497.20	1,485.43	310.58	701.18
4	2,491.67	1,491.30	304.67	695.70
5	2,503.65	1,489.08	308.63	705.93
6	2,491.53	1,487.53	309.03	694.97
7	2,497.90	1,483.10	311.15	703.65
8	2,493.17	1,483.37	304.10	705.70
9	2,505.03	1,493.50	308.05	703.48
10	2,502.12	1,493.50	305.67	702.95
11	2,502.67	1,495.58	306.23	700.85
12	2,497.62	1,487.67	310.00	699.95
Average	2,498.26	1,489.01	307.81	701.44

Repeatability 1 LRT – I/O Request Throughput Distribution Data

Repeatability 1 LRT – I/O Request Throughput Distribution Graph



SPC BENCHMARK 1[™] V1.14 Dell, Inc. Dell EqualLogic PS6210XV Array FULL DISCLOSURE REPORT

50 BSUs	Start	Stop	Interval	Duration
Start-Up/Ramp-Up	2:31:50	2:34:50	0-2	0:03:00
Measurement Interval	2:34:50	2:44:50	3-12	0:10:00
60 second intervals	All ASUs	ASU1	ASU2	ASU3
0	2.24	3.01	2.26	0.58
1	2.21	2.98	2.33	0.52
2	2.33	3.17	2.39	0.52
3	2.21	2.97	2.33	0.54
4	2.16	2.88	2.32	0.53
5	2.23	3.00	2.33	0.57
6	2.31	3.11	2.52	0.52
7	2.21	2.99	2.41	0.49
8	2.15	2.87	2.33	0.56
9	2.20	2.98	2.27	0.52
10	2.34	3.19	2.41	0.51
11	2.15	2.89	2.26	0.52
12	2.11	2.80	2.32	0.54
Average	2.21	2.97	2.35	0.53

Repeatability 1 LRT –Average Response Time (ms) Distribution Data

Repeatability 1 LRT -Average Response Time (ms) Distribution Graph



SPC BENCHMARK 1[™] V1.14 Dell, Inc. Dell EqualLogic PS6210XV Array FULL DISCLOSURE REPORT

503 BSUs	Start	Stop	Interval	Duration
Start-Up/Ramp-Up	2:44:56	2:47:57	0-2	0:03:01
Measurement Interval	2:47:57	2:57:57	3-12	0:10:00
60 second intervals	All ASUs	ASU1	ASU2	ASU3
0	25,149.83	14,978.28	3,099.20	7,072.35
1	25,158.68	14,999.27	3,088.30	7,071.12
2	25,160.13	14,992.47	3,089.93	7,077.73
3	25,131.08	14,976.38	3,109.05	7,045.65
4	25,145.90	14,983.85	3,103.90	7,058.15
5	25,163.92	14,986.58	3,094.10	7,083.23
6	25,144.55	14,998.52	3,081.72	7,064.32
7	25,119.45	14,965.87	3,087.13	7,066.45
8	25,159.62	14,975.22	3,100.10	7,084.30
9	25,133.07	14,982.42	3,088.67	7,061.98
10	25,168.60	14,996.20	3,094.82	7,077.58
11	25,160.92	14,989.05	3,099.33	7,072.53
12	25,148.47	14,994.53	3,086.27	7,067.67
Average	25,147.56	14,984.86	3,094.51	7,068.19

Repeatability 1 IOPS – I/O Request Throughput Distribution Data

Repeatability 1 IOPS – I/O Request Throughput Distribution Graph



SPC BENCHMARK 1[™] V1.14 Dell, Inc. Dell EqualLogic PS6210XV Array FULL DISCLOSURE REPORT

503 BSUs	Start	Stop	Interval	Duration
Start-Up/Ramp-Up	2:44:56	2:47:57	0-2	0:03:01
Measurement Interval	2:47:57	2:57:57	3-12	0:10:00
60 second intervals	All ASUs	ASU1	ASU2	ASU3
0	5.12	6.64	8.49	0.44
1	7.28	9.27	13.21	0.46
2	9.83	12.46	18.55	0.46
3	8.46	10.67	15.91	0.47
4	7.97	9.91	15.67	0.45
5	8.53	10.67	16.67	0.45
6	8.54	10.71	16.49	0.44
7	7.81	9.82	14.86	0.45
8	8.55	10.76	16.31	0.46
9	8.03	10.07	15.45	0.45
10	8.87	11.14	17.05	0.50
11	8.49	10.64	16.43	0.45
12	8.50	10.66	16.31	0.50
Average	8.37	10.51	16.12	0.46

Repeatability 1 IOPS –Average Response Time (ms) Distribution Data

Repeatability 1 IOPS -Average Response Time (ms) Distribution Graph



SPC BENCHMARK 1[™] V1.14 Dell, Inc. Dell EqualLogic PS6210XV Array FULL DISCLOSURE REPORT

50 BSUs	Start	Stop	Interval	Duration
Start-Up/Ramp-Up	2:58:05	3:01:05	0-2	0:03:00
Measurement Interval	3:01:05	3:11:05	3-12	0:10:00
60 second intervals	All ASUs	ASU1	ASU2	ASU3
0	2,496.30	1,489.83	306.17	700.30
1	2,506.47	1,494.70	309.82	701.95
2	2,490.23	1,482.32	307.38	700.53
3	2,505.58	1,489.50	308.78	707.30
4	2,514.45	1,496.50	311.72	706.23
5	2,501.63	1,491.75	306.90	702.98
6	2,494.40	1,485.03	306.80	702.57
7	2,496.53	1,490.50	309.82	696.22
8	2,497.05	1,491.53	308.08	697.43
9	2,490.95	1,486.78	305.77	698.40
10	2,499.07	1,492.10	308.53	698.43
11	2,505.80	1,497.70	306.77	701.33
12	2,506.95	1,492.45	307.65	706.85
Average	2,501.24	1,491.39	308.08	701.78

Repeatability 2 LRT – I/O Request Throughput Distribution Data

Repeatability 2 LRT – I/O Request Throughput Distribution Graph



SPC BENCHMARK 1[™] V1.14 Dell, Inc. Dell EqualLogic PS6210XV Array FULL DISCLOSURE REPORT

50 BSUs	Start	Stop	Interval	Duration
Start-Up/Ramp-Up	2:58:05	3:01:05	0-2	0:03:00
Measurement Interval	3:01:05	3:11:05	3-12	0:10:00
60 second intervals	All ASUs	ASU1	ASU2	ASU3
0	2.67	3.60	2.87	0.61
1	2.35	3.18	2.40	0.56
2	2.20	2.96	2.27	0.56
3	2.17	2.94	2.28	0.51
4	2.26	3.04	2.38	0.54
5	2.24	3.03	2.42	0.50
6	2.13	2.88	2.24	0.50
7	2.17	2.91	2.25	0.54
8	2.18	2.91	2.30	0.55
9	2.28	3.07	2.39	0.57
10	2.21	2.97	2.35	0.54
11	2.17	2.94	2.27	0.48
12	2.18	2.93	2.34	0.53
Average	2.20	2.96	2.32	0.53

Repeatability 2 LRT –Average Response Time (ms) Distribution Data

Repeatability 2 LRT -Average Response Time (ms) Distribution Graph



SPC BENCHMARK 1[™] V1.14 Dell, Inc. Dell EqualLogic PS6210XV Array FULL DISCLOSURE REPORT

503 BSUs	Start	Stop	Interval	Duration
Start-Up/Ramp-Up	3:11:11	3:14:12	0-2	0:03:01
Measurement Interval	3:14:12	3:24:12	3-12	0:10:00
60 second intervals	All ASUs	ASU1	ASU2	ASU3
0	25,142.70	14,999.32	3,085.95	7,057.43
1	25,165.68	15,000.05	3,096.57	7,069.07
2	25,117.53	14,968.42	3,105.63	7,043.48
3	25,180.15	15,000.17	3,091.47	7,088.52
4	25,164.25	15,011.23	3,085.10	7,067.92
5	25,151.20	14,996.47	3,087.83	7,066.90
6	25,169.78	14,998.77	3,104.48	7,066.53
7	25,139.33	14,989.57	3,082.03	7,067.73
8	25,159.40	14,991.72	3,097.83	7,069.85
9	25,189.00	15,029.42	3,097.52	7,062.07
10	25,199.90	15,007.52	3,096.58	7,095.80
11	25,163.03	15,006.50	3,091.12	7,065.42
12	25,151.68	14,981.10	3,103.45	7,067.13
Average	25,166.77	15,001.25	3,093.74	7,071.79

Repeatability 2 IOPS – I/O Request Throughput Distribution Data

Repeatability 2 IOPS – I/O Request Throughput Distribution Graph



SPC BENCHMARK 1[™] V1.14 Dell, Inc. Dell EqualLogic PS6210XV Array FULL DISCLOSURE REPORT

503 BSUs	Start	Stop	Interval	Duration
Start-Up/Ramp-Up	3:11:11	3:14:12	0-2	0:03:01
Measurement Interval	3:14:12	3:24:12	3-12	0:10:00
60 second intervals	All ASUs	ASU1	ASU2	ASU3
0	5.16	6.69	8.47	0.45
1	7.39	9.32	13.90	0.45
2	9.56	12.05	18.16	0.47
3	8.80	11.09	16.79	0.46
4	8.95	11.18	17.53	0.46
5	8.20	10.25	15.92	0.46
6	8.21	10.18	16.31	0.45
7	9.14	11.40	18.16	0.43
8	8.45	10.50	16.74	0.45
9	8.42	10.49	16.48	0.47
10	8.14	10.13	16.07	0.46
11	8.77	10.92	17.17	0.53
12	8.91	11.18	16.98	0.55
A verage	8.60	10.73	16.81	0.47

Repeatability 2 IOPS –Average Response Time (ms) Distribution Data

Repeatability 2 IOPS - Average Response Time (ms) Distribution Graph



SPC BENCHMARK 1[™] V1.14 Dell, Inc. Dell EqualLogic PS6210XV Array FULL DISCLOSURE REPORT

Repeatability 1 (LRT) Measured Intensity Multiplier and Coefficient of Variation

<u>Clause 3.4.3</u>

IM – *Intensity Multiplier:* The ratio of I/Os for each I/O stream relative to the total I/Os for all I/O streams (ASU1-1 – ASU3-1) as required by the benchmark specification.

Clauses 5.1.10 and 5.3.15.2

MIM – Measured Intensity Multiplier: The Measured Intensity Multiplier represents the ratio of measured I/Os for each I/O stream relative to the total I/Os measured for all I/O streams (ASU1-1 – ASU3-1). This value may differ from the corresponding Expected Intensity Multiplier by no more than 5%.

<u>Clause 5.3.15.3</u>

COV – **Coefficient of Variation:** This measure of variation for the Measured Intensity Multiplier cannot exceed 0.2.

	ASU1-1	ASU1-2	ASU1-3	ASU1-4	ASU2-1	ASU2-2	ASU2-3	ASU3-1
ІМ	0.0350	0.2810	0.0700	0.2100	0.0180	0.0700	0.0350	0.2810
MIM	0.0351	0.2810	0.0700	0.2100	0.0179	0.0702	0.0351	0.2808
COV	0.013	0.004	0.005	0.004	0.021	0.009	0.012	0.004

Repeatability 1 (IOPS)

Measured Intensity Multiplier and Coefficient of Variation

	ASU1-1	ASU1-2	ASU1-3	ASU1-4	ASU2-1	ASU2-2	ASU2-3	ASU3-1
ІМ	0.0350	0.2810	0.0700	0.2100	0.0180	0.0700	0.0350	0.2810
MIM	0.0350	0.2810	0.0700	0.2098	0.0180	0.0701	0.0350	0.2811
COV	0.003	0.001	0.002	0.002	0.009	0.003	0.004	0.001

Repeatability 2 (LRT) Measured Intensity Multiplier and Coefficient of Variation

	ASU1-1	ASU1-2	ASU1-3	ASU1-4	ASU2-1	ASU2-2	ASU2-3	ASU3-1
ІМ	0.0350	0.2810	0.0700	0.2100	0.0180	0.0700	0.0350	0.2810
MIM	0.0351	0.2809	0.0699	0.2104	0.0180	0.0699	0.0352	0.2806
COV	0.010	0.003	0.009	0.005	0.022	0.008	0.009	0.004

	ASU1-1	ASU1-2	ASU1-3	ASU1-4	ASU2-1	ASU2-2	ASU2-3	ASU3-1
IM	0.0350	0.2810	0.0700	0.2100	0.0180	0.0700	0.0350	0.2810
MIM	0.0349	0.2809	0.0701	0.2101	0.0180	0.0699	0.0350	0.2810
COV	0.004	0.001	0.003	0.002	0.005	0.003	0.004	0.001

Repeatability 2 (IOPS) Measured Intensity Multiplier and Coefficient of Variation

Data Persistence Test

<u>Clause 6</u>

The Data Persistence Test demonstrates the Tested Storage Configuration (TSC):

- Is capable of maintain data integrity across a power cycle.
- Ensures the transfer of data between Logical Volumes and host systems occurs without corruption or loss.

The SPC-1 Workload Generator will write 16 block I/O requests at random over the total Addressable Storage Capacity of the TSC for ten (10) minutes at a minimum of 25% of the load used to generate the SPC-1 IOPSTM primary metric. The bit pattern selected to be written to each block as well as the address of the block will be retained in a log file.

The Tested Storage Configuration (TSC) will be shutdown and restarted using a power off/power on cycle at the end of the above sequence of write operations. In addition, any caches employing battery backup must be flushed/emptied.

The SPC-1 Workload Generator will then use the above log file to verify each block written contains the correct bit pattern.

<u>Clause 9.4.3.8</u>

The following content shall appear in this section of the FDR:

- 1. A listing or screen image of all input parameters supplied to the Workload Generator.
- 2. For the successful Data Persistence Test Run, a table illustrating key results. The content, appearance, and format of this table are specified in Table 9-12. Information displayed in this table shall be obtained from the Test Run Results File referenced below in #3.
- 3. For the successful Data Persistence Test Run, the human readable Test Run Results file produced by the Workload Generator (may be contained in an appendix).

SPC-1 Workload Generator Input Parameters

The SPC-1 Workload Generator input parameters for the Sustainability, IOPS, Response Time Ramp, Repeatability, and Persistence Test Runs are documented in <u>Appendix</u> <u>E: SPC-1 Workload Generator Input Parameters</u> on Page <u>82</u>.

Data Persistence Test Results File

A link to each test result file generated from each Data Persistence Test is listed below. <u>Persistence 1 Test Results File</u> <u>Persistence 2 Test Results File</u>

Data Persistence Test Results

Data Persistence Test Results							
Data Persistence Test Run Number: 1							
Total Number of Logical Blocks Written	60,015,312						
Total Number of Logical Blocks Verified 52,8							
Total Number of Logical Blocks that Failed Verification	0						
Time Duration for Writing Test Logical Blocks	10 minutes						
Size in bytes of each Logical Block 512							
Number of Failed I/O Requests in the process of the Test	0						

In some cases the same address was the target of multiple writes, which resulted in more Logical Blocks Written than Logical Blocks Verified. In the case of multiple writes to the same address, the pattern written and verified must be associated with the last write to that address.

PRICED STORAGE CONFIGURATION AVAILABILITY DATE

<u>Clause 9.4.3.9</u>

The committed delivery data for general availability (Availability Date) of all products that comprise the Priced Storage Configuration must be reported. When the Priced Storage Configuration includes products or components with different availability dates, the reported Availability Date for the Priced Storage Configuration must be the date at which all components are committed to be available.

The Dell EqualLogic PS6210XV Array as documented in this Full Disclosure Report is currently available for customer purchase and shipment.

PRICING INFORMATION

<u>Clause 9.4.3.3.6</u>

The Executive Summary shall contain a pricing spreadsheet as documented in Clause 8.3.1.

Pricing information may be found in the Priced Storage Configuration Pricing section on page 17.

TESTED STORAGE CONFIGURATION (TSC) AND PRICED STORAGE CONFIGURATION DIFFERENCES

Clause 9.4.3.3.8

The Executive Summary shall contain a list of all differences between the Tested Storage Configuration (TSC) and the Priced Storage Configuration.

A list of all differences between the Tested Storage Configuration (TSC) and Priced Storage Configuration may be found in the Executive Summary portion of this document on page 17.

ANOMALIES OR IRREGULARITIES

<u>Clause 9.4.3.10</u>

The FDR shall include a clear and complete description of any anomalies or irregularities encountered in the course of executing the SPC-1 benchmark that may in any way call into question the accuracy, verifiability, or authenticity of information published in this FDR.

There were no anomalies or irregularities encountered during the SPC-1 Onsite Audit of the Dell EqualLogic PS6210XV Array.

APPENDIX A: SPC-1 GLOSSARY

"Decimal" (powers of ten) Measurement Units

In the storage industry, the terms "kilo", "mega", "giga", "tera", "peta", and "exa" are commonly used prefixes for computing performance and capacity. For the purposes of the SPC workload definitions, all of the following terms are defined in "powers of ten" measurement units.

A kilobyte (KB) is equal to $1,000 (10^3)$ bytes.

A megabyte (MB) is equal to 1,000,000 (10⁶) bytes.

A gigabyte (GB) is equal to 1,000,000,000 (10⁹) bytes.

A terabyte (TB) is equal to 1,000,000,000,000 (10¹²) bytes.

A petabyte (PB) is equal to 1,000,000,000,000,000 (10¹⁵) bytes

An exabyte (EB) is equal to 1,000,000,000,000,000 (10¹⁸) bytes

"Binary" (powers of two) Measurement Units

The sizes reported by many operating system components use "powers of two" measurement units rather than "power of ten" units. The following standardized definitions and terms are also valid and may be used in this document.

A kibibyte (KiB) is equal to 1,024 (2¹⁰) bytes.

A mebibyte (MiB) is equal to 1,048,576 (2²⁰) bytes.

A gigibyte (GiB) is equal to 1,073,741,824 (2³⁰) bytes.

A tebibyte (TiB) is equal to 1,099,511,627,776 (2⁴⁰) bytes.

A pebibyte (PiB) is equal to 1,125,899,906,842,624 (2⁵⁰) bytes.

An exbibyte (EiB) is equal to 1,152,921,504,606,846,967 (2⁶⁰) bytes.

SPC-1 Data Repository Definitions

Total ASU Capacity: The total storage capacity read and written in the course of executing the SPC-1 benchmark.

Application Storage Unit (ASU): The logical interface between the storage and SPC-1 Workload Generator. The three ASUs (Data, User, and Log) are typically implemented on one or more Logical Volume.

Logical Volume: The division of Addressable Storage Capacity into individually addressable logical units of storage used in the SPC-1 benchmark. Each Logical Volume is implemented as a single, contiguous address space.

Addressable Storage Capacity: The total storage (sum of Logical Volumes) that can be read and written by application programs such as the SPC-1 Workload Generator.

FULL DISCLOSURE REPORT

Configured Storage Capacity: This capacity includes the Addressable Storage Capacity and any other storage (parity disks, hot spares, etc.) necessary to implement the Addressable Storage Capacity.

Physical Storage Capacity: The formatted capacity of all storage devices physically present in the Tested Storage Configuration (TSC).

Data Protection Overhead: The storage capacity required to implement the selected level of data protection.

Required Storage: The amount of Configured Storage Capacity required to implement the Addressable Storage Configuration, excluding the storage required for the three ASUs.

Global Storage Overhead: The amount of Physical Storage Capacity that is required for storage subsystem use and unavailable for use by application programs.

Total Unused Storage: The amount of storage capacity available for use by application programs but not included in the Total ASU Capacity.

SPC-1 Data Protection Levels

Protected 1: The single point of failure of any *storage device* in the configuration will not result in permanent loss of access to or integrity of the SPC-1 Data Repository.

Protected 2: The single point of failure of any *component* in the configuration will not result in permanent loss of access to or integrity of the SPC-1 Data Repository.

SPC-1 Test Execution Definitions

Average Response Time: The sum of the Response Times for all Measured I/O Requests divided by the total number of Measured I/O Requests.

Completed I/O Request: An I/O Request with a Start Time and a Completion Time (see "I/O Completion Types" below).

Completion Time: The time recorded by the Workload Generator when an I/O Request is satisfied by the TSC as signaled by System Software.

Data Rate: The data transferred in all Measured I/O Requests in an SPC-1 Test Run divided by the length of the Test Run in seconds.

Expected I/O Count: For any given I/O Stream and Test Phase, the product of 50 times the BSU level, the duration of the Test Phase in seconds, and the Intensity Multiplier for that I/O Stream.

Failed I/O Request: Any I/O Request issued by the Workload Generator that could not be completed or was signaled as failed by System Software. A Failed I/O Request has no Completion Time (see "I/O Completion Types" below).

I/O Request Throughput: The total number of Measured I/O requests in an SPC-1 Test Run divided by the duration of the Measurement Interval in seconds.

In-Flight I/O Request: An I/O Request issued by the I/O Command Generator to the TSC that has a recorded Start Time, but does not complete within the Measurement Interval (see "I/O Completion Types" below).

Measured I/O Request: A Completed I/O Request with a Completion Time occurring within the Measurement Interval (see "I/O Completion Types" below).

Measured Intensity Multiplier: The percentage of all Measured I/O Requests that were issued by a given I/O Stream.

Measurement Interval: The finite and contiguous time period, after the TSC has reached Steady State, when data is collected by a Test Sponsor to generate an SPC-1 test result or support an SPC-1 test result.

Ramp-Up: The time required for the Benchmark Configuration (BC) to produce Steady State throughput after the Workload Generator begins submitting I/O Requests to the TSC for execution.

Ramp-Down: The time required for the BC to complete all I/O Requests issued by the Workload Generator. The Ramp-Down period begins when the Workload Generator ceases to issue new I/O Requests to the TSC.

Response Time: The Response Time of a Measured I/O Request is its Completion Time minus its Start Time.

Start Time: The time recorded by the Workload Generator when an I/O Request is submitted, by the Workload Generator, to the System Software for execution on the Tested Storage Configuration (TSC).

Start-Up: The period that begins after the Workload Generator starts to submit I/O requests to the TSC and ends at the beginning of the Measurement Interval.

Shut-Down: The period between the end of the Measurement Interval and the time when all I/O Requests issued by the Workload Generator have completed or failed.

Steady State: The consistent and sustainable throughput of the TSC. During this period the load presented to the TSC by the Workload Generator is constant.

Test: A collection of Test Phases and or Test Runs sharing a common objective.

Test Run: The execution of SPC-1 for the purpose of producing or supporting an SPC-1 test result. SPC-1 Test Runs may have a finite and measured Ramp-Up period, Start-Up period, Shut-Down period, and Ramp-Down period as illustrated in the "SPC-1 Test Run Components" below. All SPC-1 Test Runs shall have a Steady State period and a Measurement Interval.

Test Phase: A collection of one or more SPC-1 Test Runs sharing a common objective and intended to be run in a specific sequence.

I/O Completion Types



SPC-1 Test Run Components



FULL DISCLOSURE REPORT

APPENDIX B: CUSTOMER TUNABLE PARAMETERS AND OPTIONS

There were no customer tunable parameter or options changed from their default values. Firmware auto-tunes critical performance affecting parameters.

APPENDIX C: TESTED STORAGE CONFIGURATION (TSC) CREATION

The Dell EqualLogic Group Manager GUI was used to create and configure the Tested Storage Configuration (TSC). The Dell EqualLogic Host Integration Tools for Windows was installed on the Host System. The Group Manager GUI also required installation of Java.

Starting the Group Manager GUI:



- 1. Start a web browser on the Host System where the Dell EqualLogic Integration Tools are installed.
- 2. Start the Group Manager GUI by entering the IP Address of the Dell EqualLogic 6210XV in the address bar of the web browser.

SPC BENCHMARK 1™ V1.14FULL DISCLOSURE REPORTDell, Inc.Dell EqualLogic PS6210XV Array

- 3. Perform the following to logon to the Group Manager GUI as illustrated above:
 - a. Enter grpadmin in the User name box.
 - b. Enter the password of the user account entered above in the **Password** box.
 - c. Click Log In to open the Group Manager GUI.

Create Custom Storage Pool

XYguys - EqualLogic Group Mr	anager - Windows Internet Explo	rer
Group II+	Storage pool default	<u>arzestmin</u> Logged in 4/29/14 11:34 PM <u>Log oxf</u>
Group XVguys	Activities	Status Volumes
Refresh data	🔇 Pool default 🛛 🔺	General Pool Information
Create storage pool	Administration Modify pool settings Volumes <u>Create volume</u>	Members Volumes Snapshots Total 0 Total 0 Members online 0 Volumes online 0 Members in use 0 Volumes in use 0 Members in use 0 Snapshots online 0 SCSI connections 0 Snapshots in use 0
		Pool Disk Space
		Pool space by use Reclaimable an
	*	Total 0 MB Oversubscribed p Volume reserve 0 MB Oversubscribed p Snapshot reserve 0 MB Oversubscribed p Delegated 0 MB Storage containers Free 0 MB Oversubscribed p
		Pool Members
		Total members in storage poot 0
		Member Capacity Free RAD Number Member space policy of disks status
Group		None

1. By default, there is a **default** pool created by the storage system. To create a custom pool, right click on **Storage Pools** and select **Create storage pool** as illustrated above.

Freate storage pool				×		
1 - Pool Settings				9		
> 1 - General	General pr	General properties				
2	* <u>N</u> ame: Description:	CustomPool				
3						
		Back Ne	xt Einish	Cancel		

2. Enter the desired pool name as illustrated above.

Treat

2 - Pool Members					3
- General	Pool memb	ers			
2 - Pool Members	Member	Storage pool	Capacity	Free space	RAID policy
	○ XV-2	5-guys	2.84 TB	1.01 TB	RAID 10
	O XV-3	5-guys	2.84 TB	1.01 TB	RAID 10
	XV-1	5-guys	2.84 TB	1.01 TB	RAID 10
	51101.0	ide bool deraur	Curren	t New	Change
	Total pool o	ge pool derauk	Currer	nt New	Change
	Total pool s Free pool s	pace pace	Currer 0 0	it New MB 0 MB 0	Change MB 0 MB MB 0 MB
	Total pool s	ge pool derauit pace pace pace pool 5-cuvs	Currer 0 0 Currer	nt New MB 0 MB 0	Change MB 0 MB MB 0 MB Change
	Total pool s Free pool s Store Total pool s	ige pool derauit pace lige pool 5-guys pace	Currer 0 Currer 8.52	t New MB 0 MB 0 1t New 11 5.68	Change MB 0 MB MB 0 MB Change TB -2.84 TB
	Total pool s Free pool s Store Total pool s Free pool s	ge pool derauit pace pace ige pool 5-guys pace pace	Currer 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	nt New MB 0 MB 0 nt New TB 5.68 TB 205.68	Change MB 0 MB MB 0 MB Change TB -2.84 TE GB -2.84 TE
	Total pool s Free pool s Story Total pool s Free pool s New sto	ige pool derauit pace ige pool 5-guys pace pace rage pool Scott	Currer 0 0 Currer 8.52 3.04	nt New MB 0 MB 0 MB 0 MB 5.68 TB 5.68	Change MB 0 MB MB 0 MB Change ITB -2.84 TE GB -2.84 TE
	Total pool s Free pool s Store Total pool s Free pool s New sto Stor	ge pool derauit pace age pool 5-guys pace pace pace rage pool Scott age pool Scott	Currer 0 Currer 8.52 3.04 Currer	t New MB 0 MB 0 t New TB 5.68 TB 205.68	Change MB 0 MB Change TB -2.84 TE GB -2.84 TE
	Total pool s Free pool s Total pool s Free pool s Free pool s New sto Stor Total pool s	ge pool derauit pace pace pace pace pace pace rage pool Scott pace	Currer 0 Currer 8.52 3.04 Currer 0	t New MB 0 MB 0 t New TB 5.68 TB 205.68 t New MB 2.84	Change MB 0 MB Change TB -2.84 TE GB -2.84 TE Change TB 2.84 TB

3. Select the 3 PS6210XV Array the member used for the TSC, repeating the operation for each member.

Next

Einish

Cancel

Back

A summary screenshot of the storage pool and 3 members appears below.



Creating SPC-1 Volumes

1. The TSC's SPC-1 Logical Volumes are created by clicking on **Volumes**, which appears in the above summary screenshot, then right clickling on **Volumes** and then **Create volume** as illustrated below.

😂 XVguys - Equal G 💽 🗢 🔁 h	Logic Group Manager - W	indows Internet Explo	avail.ogic Group M	×			• ☆ ©
Deell E	qualLogic Group	grpadmin Logged in 4/29/14 3.39 PM Log.out					
Uolumes	🗐 🕶 💙 Vol	umes			<u>@</u>	🔊 😋 🔇	0 0
Group XVguys	Refresh data	ies	Volumes				
E-Custom S	Create volume	nes 🔺	Total volumes . Online volumes	0			
-	Create volume folder	volume volume folder recovery bin	View: Overvie	w •			
L	Manage recovery bin		Volume	▲ Status	Storage	Reported	Replication
			None				
	*						

2. Name the volume **spc1**, select the previously created pool. Specify a volume capacity of 630 GB and ensure the **Thin provisioned volume** checkbox is UNCHECKED. The snapshot reserve percentage (%) should be set to zero (0). The above operations are illustrated in the following two screenshots.

Create volume					×
1 - Volume Settings					?
> 1 - General	General propertie	8			
3	Description:				
4	Folder	folder:			Ŧ
5	Storage pool assi	gnment			
	Storage pool	Capacity	Free	Drives	Pool encryption
	S-guys		8.52 TB	8.52 TB SAS HDD	None
			[Back Next S	Skip to end

Create volume					×
2 - Space					?
1 - General	~	ہر Volume space			
> 2 - Space		* Volume size: 630 GB V (md	x, 8.51 TB) below to adjust settings)		
		Snapshot space			
4		Snapshot reserve (% of volume reserve	1 0		
5		😝 Reported volume size 630 GB			155
			Free 630 GB	8	
		SEstimated changes in storage p	ool 5-guys		121
		Storage pool 5-guys	Current	New	Change
		Volume reserve	0 MB	630 GB	630 GB
		Snapshot reserve	0.008	0.06	0.00
		Delegated space	0.46	0.005	0.00
		Free pool space	8.52 TB	7.9 TB	-630 GB
		Available for borrowing	7.93 TB	7.32 TB	-630 GB
			84	ick Next	Skip to end Cancel

SPC BENCHMARK 1[™] V1.14 Dell, Inc. Dell EqualLogic PS6210XV Array FULL DISCLOSURE REPORT
APPENDIX C: TESTED STORAGE CONFIGURATION (TSC) CREATION

3. Select an access policy to allow public access to all the volumes for the TSC. Click **New** on the screenshot below to create a new universal access policy. Supply a name to the new universal access policy and specify "*.*.*.*" to provide access to all IP addresses. Click **OK** to return to the **Define iSCSI access points** screen. Select the new access policy, click **Add** and click **Skip to End** to create the volume, then click **Finish**. The above operations are illustrated in the next series of five screenshots.

Create volume								Þ
3 - Define iSCSI ac	cess poi	nts						0
1 - General	~	What kind of access ty	pe do you want for this volum	e?				
2 - Space		Cogy access controls	s from another volume ss control policies					
> 3 - iSCSI access		Define one or more ba	asic access points					
4		Pick one or more acce	cess)					
5		Agcess Policies	Access Policy groups					
		Available:	New Edit		Selected			Edit
		📑 wild30		Add >	Policy	🔺 Туре	Applies to	
		📑 wild		< Bemove	Brain	Policy	Volumes and	i snapshots 👻
		bo you want to allow s	amuitaneous access to this w	nume from more t	nan one ISCS	initiator?		
		© Yes						
		N2 N						
				Back	Ne	st Sk	ip to end	Cancel

ell EqualLogic Gro	up Manager		×
New Access	Policy		
• Name:			
OpenAccess			
Description:			
Access points: (0 o	f 16)		
CHAP account	iSCSI initiator	IP addresses	So New
None			2 Mulify
			X Delete
		OK Cance	el <u>H</u> elp

SPC BENCHMARK 1[™] V1.14 Dell, Inc. Dell EqualLogic PS6210XV Array FULL DISCLOSURE REPORT

APPENDIX C:

TESTED STORAGE CONFIGURATION (TSC) CREATION

Dell EqualLogic Group Mana	ger			×
New Extended Acces	s	Point		
You must supply at least one o CHAP Account Name:	of the	e follow	ing:	
P Addresses: (0 of 16) None	•		d fy lete	
	Ţ	07	Curvel	(Hele)

Dell EqualLogic Group Mar	ager	Þ
New Extended Acc	ess Point	
You must supply at least on CHAP Account Name:	e of the following:	
ISCSI Initiator Name:		
P Addresses: (1 of 16)	▲ ② Add Modify Delete	
	• OK Cancel	Help

Create volume						×
4 - Summary						0
1 - General	~	General settings Volume name sport				Copy
2 - Space	1	Storage pool				
3 - ISCSI access	~	Sector size				
> 4 - Summary		Snapshot settings Snapshot reserve				
		[Back	Mext	Einish	Cancel

SPC BENCHMARK 1[™] V1.14 Dell, Inc. Dell EqualLogic PS6210XV Array FULL DISCLOSURE REPORT

- Page 75 of 82
- 4. Clone the previous volume 7 times to create volumes **spc2** through **spc8** for ASU-1 and ASU-2. See the **Cloning a Volume** section for details of cloning a volume.
- 5. The capacity is different for ASU-3 volumes, so follow steps #2 and #3 above to create the two 285.04 GB volumes for **spc9** and **spc10**.

Cloning a Volume (logical units 2 through 10)

1. Right click on the volume that is to be cloned and select **Clone** as illustrated below.



2. Enter volume name **spc2** and click **Next**. The volume size if fixed to be same as the original, so just click **Next**. Those two operations are illustrated in the two screenshots below.

Clone volume spc1					×
1 - Volume Settings	5				9
> 1 - General	General propertie	s			
2	* Name: spc2	I			
3	Description:				
	Storage poor 5-guy	15			
4	Folder				
	Create volume in	folder:			Ψ.
	Storage pool assi	gnment Capacity	Free	Drives	Pool encryption
	🔘 default		0 MB	0 MB	None
	(O) 5-guys		8.52 118	7.9 TB SAS HUU	X None
				Back	Skip to end Cancel

Clone volume spc1					×
2 - Space					0
1 - General	×	Volume space			
> 2 - Space		* Volume <u>size:</u> 630 (me	xx. 7.9 TB)		
		Thin provisioned volume (use sliders	below to adjust settings)		
3		Spanshot space			
4		Sushanor shace			
		Shapshot reserve (% of volume reserve	b): 0		
		Paparted values aire 620 CD			160
		😝 Reported volume size 630 GB	Free 630 GB		
		30 GB Reported volume size \$30 GB	Free 630 GB		100
		 Reported volume size 630 GB Stimated changes in storage p 	Free 630 GB		1
		Reported volume size 630 GB Stimated changes in storage p Storage pool 5-guys	Free 630 GB aol 5-guys Current	New	Change
		Reported volume size 630 GB Stimated changes in storage p Storage pool 5-guys Volume reserve	Free 630 GB cool 5-guys Current 630 GB	New 1.23 TB	Change 630 GB
		Reported volume size 630 GB Storage pool 5-guys Volume reserve Snapshot reserve	Current 630 GB	New 1.23 TB 0 MB	Change 630 GB 0 MB
		Reported volume size 630 GB Storage pool 5-guys Volume reserve Snapshot reserve Replication reserve	Current 630 GB	New 1.23 TB 0 MB 0 MB	Change 630 GB 0 MB 0 MB
		Reported volume size 630 GB Storage pool 5-guys Volume reserve Snapshot reserve Replication reserve Delegated space	Current 630 GB	New 1.23 TB 0 MB 0 MB 0 MB	Change 630 GB 0 MB 0 MB
		Reported volume size 630 GB Storage pool 5-guys Volume reserve Snapshot reserve Replication reserve Delegated space Free pool space Augustance Augustance Storage pool space	Free 630 GB col 5-guys Current 630 GB 0 MB 0 MB 7.9 TB 7.9 TB 7.9 TB 7.9 TB	New 1.23 TB 0.MB 0.MB 0.MB 7.23 TB 6.7 TB	Change 630 GB 0 MB 0 MB 0 MB -630 GB -630 GB

SPC BENCHMARK 1[™] V1.14 Dell, Inc. Dell EqualLogic PS6210XV Array FULL DISCLOSURE REPORT

3. Select the **Copy access controls from another volume** and select **spc1** volume and click **Next**. At the Summary click **Finish** to create the clone. Those two operations are illustrated in the two screenshots below.

Clone volume spc1					×
3 - Define iSCSI ac	cess poi	nts			?
1 - General		What kind of access type do you wa	nt for this volume?		
2 - Space		Cogy access controls from another v Select or define access control polici	es		
> 3 - iSCSI access		 Define one or more basic access poi Nong (do not allow access) 	nts		
4		Select the volume from which to co	py access controls		
		Volumes:		Access controls:	
		Volume	 Multiple access 	ISCSI access: restricted	*
		€ spc1	No	Access policy groups: None Access policies: 1. main Basic access points: None	·
		Do you want to allow simultaneous	access to this volume from more than	one iSCSI initiator?	
		O Yes			
		N₂			
			Back	Next Skip to end	Cancel

Clone volume spc1					×
4 - Summary	k				0
1 - General 2 - Space 3 - ISCSI access > 4 - Summary	General settings Volume name spc2 Storage pool 5-guys Size 630 GB Sector size 512 bytes Description none Snapshot settings 0% of volume reserve In-use space warning limt 90% Space recovery delete oldest snapshot ISCSI access restricted Access type read-write Mutiple access not shared Access controls Copied from volume spc1				Concernent of the second secon
		Back	Next	Einish	Cancel

SPC BENCHMARK 1[™] V1.14 Dell, Inc. Dell EqualLogic PS6210XV Array FULL DISCLOSURE REPORT

Preparing the Volumes on the single Host System

- 1. On the Host System, open **iSCSI Initiator Properties** window and under **Targets** tab, connect all the Inactive targets for the volumes **spc1** through **spc10**.
- 2. Select **Enable multi-path** and click **OK**.

The above operations are illustrated below two screen shots.

RADIUS	Confi	guration		Dell EqualLogic MPIO	
Targets	Discovery	Favorite Ta	rgets	Volumes and Device	5
uick Connect					
o discover and i NS name of the	og on to a target target and then o	using a basic con lick Quick Connec	nection, t :t.	ype the IP address or	
arget:	R	•		Quick Connect	
iscovered target	s				
				Refresh	
				Status	
m.equallogic:0-a	f1ff6-93ea91cd7-	41347f851c2535	81-spc1	Inactive	
m.equallogic:0-a	f1ff6-94fa91cd7-	87b47f851c4535	81-spc2	Inactive	
m.equallogic:0-a	f1ff6-96da91cd7-	4c847f851c7535	81-spc3	Inactive	
m.equallogic:0-a	f1ff6-973a91cd7-	b5f47f851ca535	81-spc4	Inactive	
m.equallogic:0-a	f1ff6-97da91cd7-	ac247f851cd535	81-spc5	Inactive	
m.equallogic:0-a	f1ff6-984a91cd7-	5f447f851d0535	81-spc6	Inactive	
m.equallogic:0-a	f1ff6-98ca91cd7-	58347f851d3535	i81-spc7	Inactive	
m.equallogic:0-a	f1ff6-997a91cd7-	74547f851d6535	581-spc8	Inactive	1
1 <u> </u>			10 A	ك ألـــــ	
o connect using lick Connect.	advanced options	, select a target	and then	Connect	
o completely dis hen click Disconr	connect a target, lect.	select the target	and .	Disconnect	
or target proper elect the target	ties, including cor and click Propertie	figuration of ses	sions,	Properties	
or configuration he target and th	of devices associ en click Devices.	ated with a targe	et, select	Devices	
ore about basic i	SCSI connections	and targets			
		0	ж	Cancel App	lγ
				Conne	ect To
				Taro	et nam
					the second se



Advanced...

SPC BENCHMARK 1[™] V1.14 Dell, Inc. Dell EqualLogic PS6210XV Array FULL DISCLOSURE REPORT

Submission Identifier: A00144 Submitted for Review: JUNE 9, 2014

OK

c253581-spc1

X

Cancel

- 3. Use the Windows Disk Management utility to bring all the Windows "disks" online and initialized as illustrated below.
- 4. Reboot the Host System.

You must initialize a disk before	Logical Disk Manager can	access it.
Select disks:		
Disk 1		-
✓ Disk 2		
Disk 3		
Disk 4		•
Use the following partition style	for the selected disks:	
G MBR (Master Boot Record)	Ľ	
C GPT (GUID Partition Table	1	
Note: The GPT partition style is Windows. It is recommended fo Itanium-based computers.	not recognized by all previo r disks larger than 2TB, or d	ous versions of lisks used on

APPENDIX D: SPC-1 WORKLOAD GENERATOR STORAGE COMMANDS AND PARAMETERS

ASU Pre-Fill

The content of command and parameter file, used in this benchmark to execute the required ASU pre-fill, is listed below.

```
* This will produce a random data pattern of the entire LBA range using LSFR 32bit
compratio=1
* The first SPC-1/SPC-1C Logical Volume (LUN) for ASU-1
* or the first SPC-2/SPC-2C LUN for the single SPC-2/SPC-2/C ASU
sd=sd1,lun=\\.\PhysicalDrive1,threads=32
sd=sd2,lun=\\.\PhysicalDrive2,threads=32
sd=sd3,lun=\\.\PhysicalDrive3,threads=32
sd=sd4,lun=\\.\PhysicalDrive4,threads=32
sd=sd5,lun=\\.\PhysicalDrive5,threads=32
sd=sd6,lun=\\.\PhysicalDrive6,threads=32
sd=sd7,lun=\\.\PhysicalDrive7,threads=32
sd=sd8,lun=\\.\PhysicalDrive8,threads=32
sd=sd9,lun=\\.\PhysicalDrive9,threads=32
sd=sd10,lun=\\.\PhysicalDrive10,threads=32
wd=wd1,sd=sd1,rdpct=0,seekpct=-1,xfersize=128K
wd=wd2,sd=sd2,rdpct=0,seekpct=-1,xfersize=128K
wd=wd3,sd=sd3,rdpct=0,seekpct=-1,xfersize=128K
wd=wd4,sd=sd4,rdpct=0,seekpct=-1,xfersize=128K
wd=wd5,sd=sd5,rdpct=0,seekpct=-1,xfersize=128K
wd=wd6,sd=sd6,rdpct=0,seekpct=-1,xfersize=128K
wd=wd7,sd=sd7,rdpct=0,seekpct=-1,xfersize=128K
wd=wd8,sd=sd8,rdpct=0,seekpct=-1,xfersize=128K
wd=wd9,sd=sd9,rdpct=0,seekpct=-1,xfersize=128K
wd=wd10,sd=sd10,rdpct=0,seekpct=-1,xfersize=128K
*
* Repeat the above until all of the LUNs for all the ASUs have been specified.
* Use the same "lun=" entry as used in the SPC-1/SPC-1C/SPC-2/SPC-2C configuration
file.
rd=asu_prefill,wd=wd*,iorate=max,elapsed=50000,interval=10
* The above "elapsed=36000" may have to be increased to ensure
* that the pre-fill will reach the end of the LUN ("seek=-1")
* prior to the end of the specified elapsed time
```

Primary Metrics, Repeatability and SPC-1 Persistence Tests

The content of SPC-1 Workload Generator command and parameter file used in this benchmark to execute the Primary Metrics (Sustainability Test Phase, IOPS Test Phase, and Response Time Ramp Test Phase), Repeatability (Repeatability Test Phase 1 and Repeatability Test Phase 2), and SPC-1 Persistence Tests is listed below.

sd=asu1_1,lun=\\.\PHYSICALDRIVE1 sd=asu1_2,lun=\\.\PHYSICALDRIVE2 sd=asu1_3,lun=\\.\PHYSICALDRIVE3 sd=asu1_4,lun=\\.\PHYSICALDRIVE4 sd=asu2_1,lun=\\.\PHYSICALDRIVE5 sd=asu2_2,lun=\\.\PHYSICALDRIVE6 sd=asu2_3,lun=\\.\PHYSICALDRIVE7 sd=asu2_4,lun=\\.\PHYSICALDRIVE8 sd=asu3_1,lun=\\.\PHYSICALDRIVE9 sd=asu3_2,lun=\\.\PHYSICALDRIVE10

APPENDIX E: SPC-1 WORKLOAD GENERATOR INPUT PARAMETERS

The following script calls the standard **vdbench.bat** script to execute the required ASU prefill and upon completion of that first step, invoke the commands to execute the Primary Metrics Test (*Sustainability Test Phase, IOPS Test Phase, and Response Time Ramp Test Phase*), the Repeatability Test (*Repeatability Test Phase 1 and Repeatability Test Phase 2*), and SPC-1 Persistence Test Run 1 (*write phase*) in an uninterrupted sequence.

```
call C:\spc\spcPrefill\SPC_ASU-Prefill\503RC11\vdbench503rc11\vdbench.bat -f
C:\spc\spcPrefill\SPC_ASU-Prefill\503RC11\vdbench503rc11\prefill.parm -o
503BSUPreFill-%time:~0,2%.%time:~3,2%
C:\java7u5164\bin\java.exe metrics -b 503 -s 3000:180 -t 28800
C:\java7u5164\bin\java.exe repeat1 -b 503
C:\java7u5164\bin\java.exe repeat2 -b 503
C:\java7u5164\bin\java.exe persist1 -b 503
```

SPC-1 Persistence Test Run 2

The following script is executed to invoke the SPC-1 Persistence Test Run 2 (*read phase*) after completion of the required TSC power off/power on cycle.

```
C:\java7u5164\bin\java.exe persist2
```